

Application of He's parameter-expansion method to a coupled van der Pol oscillators with two kinds of time-delay coupling

Mohammad Taghi Darvishi and Samad Kheybari

Abstract—In this paper, the dynamics of a system of two van der Pol oscillators with delayed position and velocity is studied. We provide an approximate solution for this system using parameter-expansion method. Also, we obtain approximate values for frequencies of the system. The parameter-expansion method is more efficient than the perturbation method for this system because the method is independent of perturbation parameter assumption.

Keywords—Parameter-expansion method, Coupled van der Pol oscillator, Time-delay system.

I. INTRODUCTION

THE van der Pol oscillator was originally discovered by the Dutch electrical engineer and physicist Balthasar Van der Pol. Van der Pol found stable oscillations, now known as limit cycles, in electrical circuits employing vacuum tubes. To solve nonlinear oscillators many effective methods have been introduced, such as the

the variational iteration method [1], [2], [3], the Adomian decomposition method [4], [5], the homotopy perturbation method [6], [7], [8], [9], [10], spectral collocation method [11], [12], [13], [14], [15], homotopy analysis method [16], [17], [18], [19], [20], [21], [22], and the Exp-function method [23], [24], [25], [26], [27], [28]. Consider the following mathematical model of a coupled van der Pol oscillators

$$\begin{cases} \ddot{x} + \omega_1^2 x - \varepsilon(1 - x^2)\dot{x} = \varepsilon\alpha_2[y(t - \tau) + \dot{y}(t - \tau)], \\ \ddot{y} + \omega_2^2 y - \varepsilon(1 - y^2)\dot{y} = \varepsilon\alpha_1[x(t - \tau) + \dot{x}(t - \tau)], \end{cases} \quad (1)$$

where ε is a small positive parameter and ω_1 and ω_2 are linear undamped natural frequencies of x and y , respectively. Also dot shows differentiation with respect to time, t . In (1) the time delay τ is a positive constant, and two oscillators are coupled with two kinds of time-delay coupling. Li et al. [29] studied the dynamics of (1) by the method of averaging together with truncation of Taylor expansions. They determined the condition necessary for in-phase and out-phase modes, which is the condition necessary for saddle-node and Hopf bifurcation for symmetric modes.

Nonlinear oscillators with delay terms are very difficult to be solved, even more difficult for coupled systems. This paper suggests a universal method to the problem using a new technology called the parameter-expansion method, which

M.T. Darvishi: Department of Mathematics, Faculty of Science, Razi University, Kermanshah 67149, Iran. **e-mail:** darvishimt@yahoo.com.
S. Kheybari: Elm o Fann, Urmia 57157-94546, Iran, **e-mail:** damas_007@yahoo.com.

is very effective to the problem. We apply the parameter-expansion method to obtain approximate solution of system (1), also we provide numerical approximations for frequencies of x and y .

II. PARAMETER EXPANSION METHOD

Parameter-expansion method is an easy and straightforward approach to nonlinear oscillators. Anyone can apply the method to find approximation of amplitude-frequency relationship of a nonlinear oscillator only with basic knowledge of advance calculus. The basic idea of the parameter-expansion method was provided in [30] and one may find several applications of the method over various areas in [31], [32], [33], [34], [35], [36], [37], [38], [39], [40].

To apply parameter-expansion method on (1) we rewrite the system as

$$\begin{cases} x'' + \omega_1^2 x = \varepsilon x'(1 - x^2) + \varepsilon\alpha_2(y + y')(t - \tau), \\ y'' + \omega_2^2 y = \varepsilon y'(1 - y^2) + \varepsilon\alpha_1(x + x')(t - \tau). \end{cases} \quad (2)$$

In this section we consider case of $\omega_1 \neq \omega_2$, the case of $\omega_1 = \omega_2$ is considered separately in the next section. According to the parameter-expansion method, all variables x and y can be expanded into a series of an artificial parameter p such as

$$\begin{cases} x = x_0 + px_1 + p^2x_2 + \dots \\ y = y_0 + py_1 + p^2y_2 + \dots \end{cases} \quad (3)$$

where p is called a bookkeeping parameter [30]. We also expand all coefficients of the system (1) into a series of p in a similar way

$$\begin{cases} \omega_1^2 = \mu^2 + p\mu_1 + p^2\mu_2 + \dots \\ \omega_2^2 = \nu^2 + p\nu_1 + p^2\nu_2 + \dots \\ \varepsilon\alpha_1 = p\delta_{11} + p^2\delta_{12} + \dots \\ \varepsilon\alpha_2 = p\delta_{21} + p^2\delta_{22} + \dots \\ \varepsilon = p\varepsilon_1 + p^2\varepsilon_2 + \dots \end{cases} \quad (4)$$

By substituting expansions (3) and (4) into system (2), we have

$$(x_0'' + px_1'' + p^2x_2'' + \dots) + (\mu^2 + p\mu_1 + p^2\mu_2 + \dots) \times (x_0 + px_1 + p^2x_2 + \dots) = (p\varepsilon_1 + p^2\varepsilon_2 + \dots) \times (x_0' + px_1' + p^2x_2' + \dots) [1 - (x_0 + px_1 + p^2x_2 + \dots)^2] + (p\delta_{21} + p^2\delta_{22} + \dots) [(y_0 + py_1 + p^2y_2 + \dots) + (y_0' + py_1' + p^2y_2' + \dots)](t - \tau),$$

$$(y_0'' + py_1'' + p^2y_2'' + \dots) + (\nu^2 + p\nu_1 + p^2\nu_2 + \dots) \times (y_0 + py_1 + p^2y_2 + \dots) = (p\varepsilon_1 + p^2\varepsilon_2 + \dots) \times (y_0' + py_1' + p^2y_2' + \dots) [1 - (y_0 + py_1 + p^2y_2 + \dots)^2] + (p\delta_{11} + p^2\delta_{12} + \dots) [(x_0 + px_1 + p^2x_2 + \dots) + (x_0' + px_1' + p^2x_2' + \dots)](t - \tau).$$

Equating in powers of p , yields

$$p^0 : \begin{cases} x_0'' + \mu^2x_0 = 0 \\ y_0'' + \nu^2y_0 = 0 \end{cases} \quad (6)$$

and

$$p^1 : \begin{cases} x_1'' + \mu^2x_1 + \mu_1x_0 = \varepsilon_1x_0'(1 - x_0^2) + \delta_{21}(y_0 + y_0')(t - \tau), \\ y_1'' + \nu^2y_1 + \nu_1y_0 = \varepsilon_1y_0'(1 - y_0^2) + \delta_{11}(x_0 + x_0')(t - \tau). \end{cases} \quad (7)$$

Solving Eq. (6), we obtain

$$\begin{cases} x_0 = A_1 \cos(\mu t) + A_2 \sin(\mu t) \\ y_0 = B_1 \cos(\nu t) + B_2 \sin(\nu t), \end{cases} \quad (8)$$

where A_1, A_2, B_1 and B_2 are arbitrary constants. Substituting (8) into (7), we obtain

$$\begin{cases} x_1'' + \mu^2x_1 = \sin(\mu t)[- \mu_1A_2 - \mu\varepsilon_1A_1 + \frac{1}{4}\mu\varepsilon_1A_1A_2^2 + \frac{1}{4}\mu\varepsilon_1A_1^3] + \cos(\mu t)[- \mu_1A_1 + \mu\varepsilon_1A_2 - \frac{1}{4}\mu\varepsilon_1A_2^3 - \frac{1}{4}\mu\varepsilon_1A_1^2A_2] + \sin(3\mu t)[- \frac{3}{4}\mu\varepsilon_1A_1A_2^2 + \frac{1}{4}\mu\varepsilon_1A_1^3] + \cos(3\mu t)[- \frac{3}{4}\mu\varepsilon_1A_1^2A_2 + \frac{1}{4}\mu\varepsilon_1A_2^3] + \sin(\nu t)[- \delta_{21}B_2\tau + \delta_{21}\nu B_1\tau] + \cos(\nu t)[- \delta_{21}B_1\tau - \delta_{21}\nu B_2\tau] + t[(\delta_{21}B_1 + \delta_{21}\nu B_2) \cos(\nu t) + (\delta_{21}B_2 - \delta_{21}\nu B_1) \sin(\nu t)] \\ y_1'' + \nu^2y_1 = \sin(\nu t)[- \nu_1B_2 - \nu\varepsilon_1B_1 + \frac{1}{4}\nu\varepsilon_1B_1B_2^2 + \frac{1}{4}\nu\varepsilon_1B_1^3] + \cos(\nu t)[- \nu_1B_1 + \nu\varepsilon_1B_2 - \frac{1}{4}\nu\varepsilon_1B_2^3 - \frac{1}{4}\nu\varepsilon_1B_1^2B_2] + \sin(3\nu t)[- \frac{3}{4}\nu\varepsilon_1B_1B_2^2 + \frac{1}{4}\nu\varepsilon_1B_1^3] + \cos(3\nu t)[- \frac{3}{4}\nu\varepsilon_1B_1^2B_2 + \frac{1}{4}\nu\varepsilon_1B_2^3] + \sin(\mu t)[- \delta_{11}A_2\tau + \delta_{11}\mu A_1\tau] + \cos(\mu t)[- \delta_{11}A_1\tau - \delta_{11}\mu A_2\tau] + t[(\delta_{11}A_1 + \delta_{11}\mu A_2) \cos(\mu t) + (\delta_{11}A_2 - \delta_{11}\mu A_1) \sin(\mu t)]. \end{cases} \quad (9)$$

If the first-order approximation be enough, then setting $p = 1$ in equations (3) and (4), we have

$$\begin{cases} x = x_0 + x_1, & \omega_1^2 = \mu^2 + \mu_1, & \varepsilon\alpha_1 = \delta_{11}, & \varepsilon = \varepsilon_1 \\ y = y_0 + y_1, & \omega_2^2 = \nu^2 + \nu_1, & \varepsilon\alpha_2 = \delta_{21}. \end{cases} \quad (10)$$

Now substituting (10) into (9) yields:

$$\begin{cases} x_1'' + \mu^2x_1 = \sin(\mu t)[- \mu_1A_2 - \mu\varepsilon A_1 + \frac{1}{4}\mu\varepsilon A_1A_2^2 + \frac{1}{4}\mu\varepsilon A_1^3] + \cos(\mu t)[- \mu_1A_1 + \mu\varepsilon A_2 - \frac{1}{4}\mu\varepsilon A_2^3 - \frac{1}{4}\mu\varepsilon A_1^2A_2] + \sin(3\mu t)[- \frac{3}{4}\mu\varepsilon A_1A_2^2 + \frac{1}{4}\mu\varepsilon A_1^3] + \cos(3\mu t)[- \frac{3}{4}\mu\varepsilon A_1^2A_2 + \frac{1}{4}\mu\varepsilon A_2^3] + \sin(\nu t)[- \varepsilon\alpha_2B_2\tau + \varepsilon\alpha_2\nu B_1\tau] + \cos(\nu t)[- \varepsilon\alpha_2B_1\tau - \varepsilon\alpha_2\nu B_2\tau] + t[(\varepsilon\alpha_2B_1 + \varepsilon\alpha_2\nu B_2) \cos(\nu t) + (\varepsilon\alpha_2B_2 - \varepsilon\alpha_2\nu B_1) \sin(\nu t)] \\ y_1'' + \nu^2y_1 = \sin(\nu t)[- \nu_1B_2 - \nu\varepsilon B_1 + \frac{1}{4}\nu\varepsilon B_1B_2^2 + \frac{1}{4}\nu\varepsilon B_1^3] + \cos(\nu t)[- \nu_1B_1 + \nu\varepsilon B_2 - \frac{1}{4}\nu\varepsilon B_2^3 - \frac{1}{4}\nu\varepsilon B_1^2B_2] + \sin(3\nu t)[- \frac{3}{4}\nu\varepsilon B_1B_2^2 + \frac{1}{4}\nu\varepsilon B_1^3] + \cos(3\nu t)[- \frac{3}{4}\nu\varepsilon B_1^2B_2 + \frac{1}{4}\nu\varepsilon B_2^3] + \sin(\mu t)[- \varepsilon\alpha_1A_2\tau + \varepsilon\alpha_1\mu A_1\tau] + \cos(\mu t)[- \varepsilon\alpha_1A_1\tau - \varepsilon\alpha_1\mu A_2\tau] + t[(\varepsilon\alpha_1A_1 + \varepsilon\alpha_1\mu A_2) \cos(\mu t) + (\varepsilon\alpha_1A_2 - \varepsilon\alpha_1\mu A_1) \sin(\mu t)]. \end{cases} \quad (11)$$

No secular term in x_1 and y_1 requires that

$$\begin{cases} -\mu_1A_2 - \mu\varepsilon A_1 + \frac{1}{4}\mu\varepsilon A_1A_2^2 + \frac{1}{4}\mu\varepsilon A_1^3 = 0, \\ -\mu_1A_1 + \mu\varepsilon A_2 - \frac{1}{4}\mu\varepsilon A_2^3 - \frac{1}{4}\mu\varepsilon A_1^2A_2 = 0, \end{cases} \quad (12)$$

and

$$\begin{cases} -\nu_1B_2 - \nu\varepsilon B_1 + \frac{1}{4}\nu\varepsilon B_1B_2^2 + \frac{1}{4}\nu\varepsilon B_1^3 = 0, \\ -\nu_1B_1 + \nu\varepsilon B_2 - \frac{1}{4}\nu\varepsilon B_2^3 - \frac{1}{4}\nu\varepsilon B_1^2B_2 = 0, \end{cases} \quad (13)$$

using (12), (13) and (10), we have

$$\begin{cases} \mu = \omega_1 \\ \nu = \omega_2. \end{cases} \quad (14)$$

The frequencies of equations are

$$\begin{cases} T_x = \frac{2\pi}{\omega_1} \\ T_y = \frac{2\pi}{\omega_2}. \end{cases} \quad (15)$$

Furthermore, (11) can be simplified as

$$\begin{cases} x_1'' + \mu^2x_1 = \sin(3\mu t)[- \frac{3}{4}\mu\varepsilon A_1A_2^2 + \frac{1}{4}\mu\varepsilon A_1^3] + \cos(3\mu t)[- \frac{3}{4}\mu\varepsilon A_1^2A_2 + \frac{1}{4}\mu\varepsilon A_2^3] + \sin(\nu t)[- \varepsilon\alpha_2B_2\tau + \varepsilon\alpha_2\nu B_1\tau] + \cos(\nu t)[- \varepsilon\alpha_2B_1\tau - \varepsilon\alpha_2\nu B_2\tau] + t[(\varepsilon\alpha_2B_1 + \varepsilon\alpha_2\nu B_2) \cos(\nu t) + (\varepsilon\alpha_2B_2 - \varepsilon\alpha_2\nu B_1) \sin(\nu t)] \\ y_1'' + \nu^2y_1 = \sin(3\nu t)[- \frac{3}{4}\nu\varepsilon B_1B_2^2 + \frac{1}{4}\nu\varepsilon B_1^3] + \cos(3\nu t)[- \frac{3}{4}\nu\varepsilon B_1^2B_2 + \frac{1}{4}\nu\varepsilon B_2^3] + \sin(\mu t)[- \varepsilon\alpha_1A_2\tau + \varepsilon\alpha_1\mu A_1\tau] + \cos(\mu t)[- \varepsilon\alpha_1A_1\tau - \varepsilon\alpha_1\mu A_2\tau] + t[(\varepsilon\alpha_1A_1 + \varepsilon\alpha_1\mu A_2) \cos(\mu t) + (\varepsilon\alpha_1A_2 - \varepsilon\alpha_1\mu A_1) \sin(\mu t)]. \end{cases} \quad (16)$$

Solving (16) yields

$$\begin{cases} x_1 = \frac{\varepsilon A_1}{32\mu} (3A_2^2 - A_1^2) \sin(3\mu t) + \frac{\varepsilon A_2}{32\mu} (3A_1^2 - A_2^2) \cos(3\mu t) \\ + \left[\frac{\varepsilon \alpha_2 (B_2 - \nu B_1)}{\mu^2 - \nu^2} t + \frac{\varepsilon \alpha_2 \tau (\mu^2 - \nu^2) (\nu B_1 - B_2) + 2\varepsilon \alpha_2 \nu (\nu B_2 + B_1)}{(\mu^2 - \nu^2)^2} \right] \sin(\nu t) \\ + \left[\frac{\varepsilon \alpha_2 (B_1 + \nu B_2)}{\mu^2 - \nu^2} t + \frac{-\varepsilon \alpha_2 \tau (\mu^2 - \nu^2) (\nu B_2 + B_1) + 2\varepsilon \alpha_2 \nu (\nu B_1 - B_2)}{(\mu^2 - \nu^2)^2} \right] \cos(\nu t), \\ y_1 = \frac{\varepsilon B_1}{32\nu} (3B_2^2 - B_1^2) \sin(3\nu t) + \frac{\varepsilon B_2}{32\nu} (3B_1^2 - B_2^2) \cos(3\nu t) \\ + \left[\frac{\varepsilon \alpha_1 (A_2 - \mu A_1)}{\nu^2 - \mu^2} t + \frac{\varepsilon \alpha_1 \tau (\nu^2 - \mu^2) (\mu A_1 - A_2) + 2\varepsilon \alpha_1 \mu (\mu A_2 + A_1)}{(\nu^2 - \mu^2)^2} \right] \sin(\mu t) \\ + \left[\frac{\varepsilon \alpha_1 (A_1 + \mu A_2)}{\nu^2 - \mu^2} t + \frac{-\varepsilon \alpha_1 \tau (\nu^2 - \mu^2) (\mu A_2 + A_1) + 2\varepsilon \alpha_1 \mu (\mu A_1 - A_2)}{(\nu^2 - \mu^2)^2} \right] \cos(\mu t). \end{cases} \quad (17)$$

Now using (17), (8) and (10) we obtain the first order solution for x and y

$$\begin{cases} x = x_0 + x_1 = A_1 \cos(\mu t) + A_2 \sin(\mu t) \\ + \frac{\varepsilon A_1}{32\mu} (3A_2^2 - A_1^2) \sin(3\mu t) + \frac{\varepsilon A_2}{32\mu} (3A_1^2 - A_2^2) \cos(3\mu t) \\ + \left[\frac{\varepsilon \alpha_2 (B_2 - \nu B_1)}{\mu^2 - \nu^2} t + \frac{\varepsilon \alpha_2 \tau (\mu^2 - \nu^2) (\nu B_1 - B_2) + 2\varepsilon \alpha_2 \nu (\nu B_2 + B_1)}{(\mu^2 - \nu^2)^2} \right] \sin(\nu t) \\ + \left[\frac{\varepsilon \alpha_2 (B_1 + \nu B_2)}{\mu^2 - \nu^2} t + \frac{-\varepsilon \alpha_2 \tau (\mu^2 - \nu^2) (\nu B_2 + B_1) + 2\varepsilon \alpha_2 \nu (\nu B_1 - B_2)}{(\mu^2 - \nu^2)^2} \right] \cos(\nu t), \\ y = y_0 + y_1 = B_1 \cos(\nu t) + B_2 \sin(\nu t) \\ + \frac{\varepsilon B_1}{32\nu} (3B_2^2 - B_1^2) \sin(3\nu t) + \frac{\varepsilon B_2}{32\nu} (3B_1^2 - B_2^2) \cos(3\nu t) \\ + \left[\frac{\varepsilon \alpha_1 (A_2 - \mu A_1)}{\nu^2 - \mu^2} t + \frac{\varepsilon \alpha_1 \tau (\nu^2 - \mu^2) (\mu A_1 - A_2) + 2\varepsilon \alpha_1 \mu (\mu A_2 + A_1)}{(\nu^2 - \mu^2)^2} \right] \sin(\mu t) \\ + \left[\frac{\varepsilon \alpha_1 (A_1 + \mu A_2)}{\nu^2 - \mu^2} t + \frac{-\varepsilon \alpha_1 \tau (\nu^2 - \mu^2) (\mu A_2 + A_1) + 2\varepsilon \alpha_1 \mu (\mu A_1 - A_2)}{(\nu^2 - \mu^2)^2} \right] \cos(\mu t). \end{cases} \quad (18)$$

III. CASE $\omega_1 = \omega_2$

In this section we suppose that $\omega_1 = \omega_2 = \omega$ and provide approximate solution of system (1) using parameter-expansion method. In this case system (1) is rewritten as

$$\begin{cases} x'' + \omega^2 x = \varepsilon x'(1 - x^2) + \varepsilon \alpha_2 (y + y')(t - \tau), \\ y'' + \omega^2 y = \varepsilon y'(1 - y^2) + \varepsilon \alpha_1 (x + x')(t - \tau). \end{cases} \quad (19)$$

As usual we expand all variables and parameters into a series of the artificial parameter p as

$$\begin{cases} x = x_0 + px_1 + p^2 x_2 + \dots \\ y = y_0 + py_1 + p^2 y_2 + \dots \\ \omega^2 = \mu^2 + p\mu_1 + p^2 \mu_2 + \dots \\ \varepsilon \alpha_1 = p\delta_{11} + p^2 \delta_{12} + \dots \\ \varepsilon \alpha_2 = p\delta_{21} + p^2 \delta_{22} + \dots \\ \varepsilon = p\varepsilon_1 + p^2 \varepsilon_2 + \dots \end{cases} \quad (20)$$

Substituting expansions (20) into system (19), and equating in powers of p , yields

$$p^0 : \begin{cases} x''_0 + \mu^2 x_0 = 0 \\ y''_0 + \mu^2 y_0 = 0 \end{cases} \quad (21)$$

and

$$p^1 : \begin{cases} x''_1 + \mu^2 x_1 + \mu_1 x_0 = \\ \varepsilon_1 x'_0 (1 - x_0^2) + \delta_{21} (y_0 + y'_0) (t - \tau), \\ y''_1 + \mu^2 y_1 + \mu_1 y_0 = \\ \varepsilon_1 y'_0 (1 - y_0^2) + \delta_{11} (x_0 + x'_0) (t - \tau). \end{cases} \quad (22)$$

Solving (21), we obtain

$$\begin{cases} x_0 = A_1 \cos(\mu t) + A_2 \sin(\mu t) \\ y_0 = B_1 \cos(\mu t) + B_2 \sin(\mu t), \end{cases} \quad (23)$$

where A_1, A_2, B_1 and B_2 are arbitrary constants. Substituting (23) into (22), yields

$$\begin{cases} x''_1 + \mu^2 x_1 = \sin(\mu t) [-\mu_1 A_2 - \mu \varepsilon_1 A_1 + \frac{1}{4} \mu \varepsilon_1 A_1 A_2^2 + \frac{1}{4} \mu \varepsilon_1 A_1^3 - \delta_{21} B_2 \tau + \delta_{21} \mu B_1 \tau] \\ + \cos(\mu t) [-\mu_1 A_1 + \mu \varepsilon_1 A_2 - \frac{1}{4} \mu \varepsilon_1 A_2^3 - \frac{1}{4} \mu \varepsilon_1 A_1^2 A_2 - \delta_{21} B_1 \tau - \delta_{21} \mu B_2 \tau] \\ + \sin(3\mu t) [-\frac{3}{4} \mu \varepsilon_1 A_1 A_2^2 + \frac{1}{4} \mu \varepsilon_1 A_1^3] \\ + \cos(3\mu t) [-\frac{3}{4} \mu \varepsilon_1 A_1^2 A_2 + \frac{1}{4} \mu \varepsilon_1 A_2^3] \\ + t[(\delta_{21} B_1 + \delta_{21} \mu B_2) \cos(\mu t) + (\delta_{21} B_2 - \delta_{21} \mu B_1) \sin(\mu t)] \\ y''_1 + \mu^2 y_1 = \sin(\mu t) [-\mu_1 B_2 - \mu \varepsilon_1 B_1 + \frac{1}{4} \mu \varepsilon_1 B_1 B_2^2 + \frac{1}{4} \mu \varepsilon_1 B_1^3 - \delta_{11} A_2 \tau + \delta_{11} \mu A_1 \tau] \\ + \cos(\mu t) [-\mu_1 B_1 + \mu \varepsilon_1 B_2 - \frac{1}{4} \mu \varepsilon_1 B_2^3 - \frac{1}{4} \mu \varepsilon_1 B_1^2 B_2 - \delta_{11} A_1 \tau - \delta_{11} \mu A_2 \tau] \\ + \sin(3\mu t) [-\frac{3}{4} \mu \varepsilon_1 B_1 B_2^2 + \frac{1}{4} \mu \varepsilon_1 B_1^3] \\ + \cos(3\mu t) [-\frac{3}{4} \mu \varepsilon_1 B_1^2 B_2 + \frac{1}{4} \mu \varepsilon_1 B_2^3] \\ + t[(\delta_{11} A_1 + \delta_{11} \mu A_2) \cos(\mu t) + (\delta_{11} A_2 - \delta_{11} \mu A_1) \sin(\mu t)]. \end{cases} \quad (24)$$

If the first-order approximation be enough, then setting $p = 1$ in equations (20), we have

$$\begin{cases} x = x_0 + x_1, & \omega^2 = \mu^2 + \mu_1, & \varepsilon \alpha_1 = \delta_{11}, \\ y = y_0 + y_1, & \varepsilon = \varepsilon_1, & \varepsilon \alpha_2 = \delta_{21}. \end{cases} \quad (25)$$

Now substituting (25) into (24) yields:

$$\begin{cases} x_1'' + \mu^2 x_1 = \\ \sin(\mu t) [-\mu_1 A_2 - \mu \varepsilon A_1 + \frac{1}{4} \mu \varepsilon A_1 A_2^2 + \\ \frac{1}{4} \mu \varepsilon A_1^3 - \varepsilon \alpha_2 B_2 \tau + \varepsilon \alpha_2 \mu B_1 \tau] \\ + \cos(\mu t) [-\mu_1 A_1 + \mu \varepsilon A_2 - \frac{1}{4} \mu \varepsilon A_2^3 - \\ \frac{1}{4} \mu \varepsilon A_1^2 A_2 - \varepsilon \alpha_2 B_1 \tau - \varepsilon \alpha_2 \mu B_2 \tau] \\ + \sin(3\mu t) [-\frac{3}{4} \mu \varepsilon A_1 A_2^2 + \frac{1}{4} \mu \varepsilon A_1^3] \\ + \cos(3\mu t) [-\frac{3}{4} \mu \varepsilon A_1^2 A_2 + \frac{1}{4} \mu \varepsilon A_2^3] \\ + t[(\varepsilon \alpha_2 B_1 + \varepsilon \alpha_2 \mu B_2) \cos(\mu t) + \\ (\varepsilon \alpha_2 B_2 - \varepsilon \alpha_2 \mu B_1) \sin(\mu t)] \\ \\ y_1'' + \mu^2 y_1 = \\ \sin(\mu t) [-\mu_1 B_2 - \mu \varepsilon B_1 + \frac{1}{4} \mu \varepsilon B_1 B_2^2 + \\ \frac{1}{4} \mu \varepsilon B_1^3 - \varepsilon \alpha_1 A_2 \tau + \varepsilon \alpha_1 \mu A_1 \tau] \\ + \cos(\mu t) [-\mu_1 B_1 + \mu \varepsilon B_2 - \frac{1}{4} \mu \varepsilon B_2^3 - \\ \frac{1}{4} \mu \varepsilon B_1^2 B_2 - \varepsilon \alpha_1 A_1 \tau - \varepsilon \alpha_1 \mu A_2 \tau] \\ + \sin(3\mu t) [-\frac{3}{4} \mu \varepsilon B_1 B_2^2 + \frac{1}{4} \mu \varepsilon B_1^3] \\ + \cos(3\mu t) [-\frac{3}{4} \mu \varepsilon B_1^2 B_2 + \frac{1}{4} \mu \varepsilon B_2^3] \\ + t[(\varepsilon \alpha_1 A_1 + \varepsilon \alpha_1 \mu A_2) \cos(\mu t) + \\ (\varepsilon \alpha_1 A_2 - \varepsilon \alpha_1 \mu A_1) \sin(\mu t)]. \end{cases} \quad (26)$$

No secular term in x_1 requires that

$$\begin{cases} -\mu_1 A_2 - \mu \varepsilon A_1 + \frac{1}{4} \mu \varepsilon A_1 A_2^2 + \frac{1}{4} \mu \varepsilon A_1^3 - \\ \varepsilon \alpha_2 B_2 \tau + \varepsilon \alpha_2 \mu B_1 \tau = 0, \\ -\mu_1 A_1 + \mu \varepsilon A_2 - \frac{1}{4} \mu \varepsilon A_2^3 - \frac{1}{4} \mu \varepsilon A_1^2 A_2 - \\ \varepsilon \alpha_2 B_1 \tau - \varepsilon \alpha_2 \mu B_2 \tau = 0 \end{cases} \quad (27)$$

then

$$\mu_1 = \frac{\varepsilon \alpha_2 \tau}{A_1^2 + A_2^2} (\mu(A_2 B_1 - A_1 B_2)) - (A_2 B_2 + A_1 B_1). \quad (28)$$

Now using $\omega^2 = \mu^2 + \mu_1$ into (28) yields:

$$\omega^2 = \mu^2 + \frac{\varepsilon \alpha_2 \tau (A_2 B_1 - A_1 B_2)}{A_1^2 + A_2^2} \mu - \frac{\varepsilon \alpha_2 \tau (A_2 B_2 + A_1 B_1)}{A_1^2 + A_2^2} \quad (29)$$

solving equation (29) with respect to μ yields

$$\mu = \frac{\varepsilon \alpha_2 \tau (A_1 B_2 - A_2 B_1) \pm K}{2(A_1^2 + A_2^2)^2} \quad (30)$$

where $K = \sqrt{K_1 + K_2}$ for $K_1 = (\varepsilon \alpha_2 \tau (A_2 B_1 - A_1 B_2))^2$ and $K_2 = 4\varepsilon \alpha_2 \tau (A_1 B_1 + A_2 B_2) (A_1^2 + A_2^2)$. No secular term in y_1 requires that

$$\begin{cases} -\mu_1 B_2 - \mu \varepsilon B_1 + \frac{1}{4} \mu \varepsilon B_1 B_2^2 + \frac{1}{4} \mu \varepsilon B_1^3 - \\ \varepsilon \alpha_1 A_2 \tau + \varepsilon \alpha_1 \mu A_1 \tau = 0, \\ -\mu_1 B_1 + \mu \varepsilon B_2 - \frac{1}{4} \mu \varepsilon B_2^3 - \frac{1}{4} \mu \varepsilon B_1^2 B_2 - \\ \varepsilon \alpha_1 A_1 \tau - \varepsilon \alpha_1 \mu A_2 \tau = 0 \end{cases} \quad (31)$$

then

$$\mu_1 = \frac{\varepsilon \alpha_1 \tau}{B_1^2 + B_2^2} (\mu(B_2 A_1 - B_1 A_2)) - (B_2 A_2 + B_1 A_1). \quad (32)$$

Now using $\omega^2 = \mu^2 + \mu_1$ into (32) yields

$$\omega^2 = \mu^2 + \frac{\varepsilon \alpha_1 \tau (B_2 A_1 - B_1 A_2)}{B_1^2 + B_2^2} \mu - \frac{\varepsilon \alpha_1 \tau (B_2 A_2 + B_1 A_1)}{B_1^2 + B_2^2} \quad (33)$$

solving equation (33) with respect to μ yields

$$\mu = \frac{E \pm F}{2(B_1^2 + B_2^2)^2} \quad (34)$$

where

$$E = \varepsilon \alpha_1 \tau (B_1 A_2 - B_2 A_1)$$

and $F = \sqrt{G + H}$ for $G = (\varepsilon \alpha_1 \tau (B_2 A_1 - B_1 A_2))^2$ and $H = 4\varepsilon \alpha_1 \tau (B_1 A_1 + B_2 A_2) (B_1^2 + B_2^2)$. The frequencies of equations are

$$\begin{cases} T_x = \frac{4\pi(A_1^2 + A_2^2)^2}{X_1 \pm \sqrt{X_2}} \\ T_y = \frac{4\pi(B_1^2 + B_2^2)^2}{Y_1 \pm \sqrt{Y_2}}. \end{cases} \quad (35)$$

where

$$\begin{aligned} X_1 &= \varepsilon \alpha_2 \tau (A_1 B_2 - A_2 B_1), \\ X_2 &= (\varepsilon \alpha_2 \tau (A_2 B_1 - A_1 B_2))^2 \\ &\quad + 4\varepsilon \alpha_2 \tau (A_1 B_1 + A_2 B_2) (A_1^2 + A_2^2), \\ Y_1 &= \varepsilon \alpha_1 \tau (B_1 A_2 - B_2 A_1) \end{aligned}$$

and

$$\begin{aligned} Y_2 &= (\varepsilon \alpha_1 \tau (B_2 A_1 - B_1 A_2))^2 \\ &\quad + 4\varepsilon \alpha_1 \tau (B_1 A_1 + B_2 A_2) (B_1^2 + B_2^2). \end{aligned}$$

Furthermore, (26) can be simplified as

$$\begin{cases} x_1'' + \mu^2 x_1 = \\ \sin(3\mu t) [-\frac{3}{4} \mu \varepsilon A_1 A_2^2 + \frac{1}{4} \mu \varepsilon A_1^3] \\ + \cos(3\mu t) [-\frac{3}{4} \mu \varepsilon A_1^2 A_2 + \frac{1}{4} \mu \varepsilon A_2^3] \\ + t[(\varepsilon \alpha_2 B_1 + \varepsilon \alpha_2 \mu B_2) \cos(\mu t) + \\ (\varepsilon \alpha_2 B_2 - \varepsilon \alpha_2 \mu B_1) \sin(\mu t)] \\ \\ y_1'' + \mu^2 y_1 = \\ \sin(3\mu t) [-\frac{3}{4} \mu \varepsilon B_1 B_2^2 + \frac{1}{4} \mu \varepsilon B_1^3] \\ + \cos(3\mu t) [-\frac{3}{4} \mu \varepsilon B_1^2 B_2 + \frac{1}{4} \mu \varepsilon B_2^3] \\ + t[(\varepsilon \alpha_1 A_1 + \varepsilon \alpha_1 \mu A_2) \cos(\mu t) + \\ (\varepsilon \alpha_1 A_2 - \varepsilon \alpha_1 \mu A_1) \sin(\mu t)]. \end{cases} \quad (36)$$

Solving (36) yields

$$\begin{cases} x_1 = \\ \frac{\varepsilon A_1}{32\mu} (3A_2^2 - A_1^2) \sin(3\mu t) + \frac{\varepsilon A_2}{32\mu} (3A_1^2 - A_2^2) \cos(3\mu t) \\ + \frac{\varepsilon \alpha_2}{4\mu} [(B_1 + \mu B_2)t^2 + (\frac{B_2}{\mu} - B_1)t] \sin(\mu t) \\ + \frac{\varepsilon \alpha_2}{4\mu} [(\mu B_1 - B_2)t^2 + (\frac{B_1}{\mu} + B_2)t] \cos(\mu t) \\ \\ y_1 = \\ \frac{\varepsilon B_1}{32\mu} (3B_2^2 - B_1^2) \sin(3\mu t) + \frac{\varepsilon B_2}{32\mu} (3B_1^2 - B_2^2) \cos(3\mu t) \\ + \frac{\varepsilon \alpha_1}{4\mu} [(A_1 + \mu A_2)t^2 + (\frac{A_2}{\mu} - A_1)t] \sin(\mu t) \\ + \frac{\varepsilon \alpha_1}{4\mu} [(\mu A_1 - A_2)t^2 + (\frac{A_1}{\mu} + A_2)t] \cos(\mu t). \end{cases} \quad (37)$$

Now using (37), (23) and (25) we obtain the first order solution of x and y

$$\begin{cases} x = x_0 + x_1 = A_1 \cos(\mu t) + A_2 \sin(\mu t) \\ + \frac{\varepsilon A_1}{32\mu} (3A_2^2 - A_1^2) \sin(3\mu t) + \frac{\varepsilon A_2}{32\mu} (3A_1^2 - A_2^2) \cos(3\mu t) \\ + \frac{\varepsilon \alpha_2}{4\mu} [(B_1 + \mu B_2)t^2 + (\frac{B_2}{\mu} - B_1)t] \sin(\mu t) \\ + \frac{\varepsilon \alpha_2}{4\mu} [(\mu B_1 - B_2)t^2 + (\frac{B_1}{\mu} + B_2)t] \cos(\mu t) \\ \\ y = y_0 + y_1 = B_1 \cos(\mu t) + B_2 \sin(\mu t) \\ + \frac{\varepsilon B_1}{32\mu} (3B_2^2 - B_1^2) \sin(3\mu t) + \frac{\varepsilon B_2}{32\mu} (3B_1^2 - B_2^2) \cos(3\mu t) \\ + \frac{\varepsilon \alpha_1}{4\mu} [(A_1 + \mu A_2)t^2 + (\frac{A_2}{\mu} - A_1)t] \sin(\mu t) \\ + \frac{\varepsilon \alpha_1}{4\mu} [(\mu A_1 - A_2)t^2 + (\frac{A_1}{\mu} + A_2)t] \cos(\mu t). \end{cases} \quad (38)$$




Fig. 1. Plots of $x = x_0 + x_1$ and $y = y_0 + y_1$ for $[\omega_1, \omega_2, \tau, \alpha_1, \alpha_2, \epsilon, x(0), \dot{x}(0), y(0), \dot{y}(0)] = [1, 3, 5, 1, 1, 0.1, 3, 0, 1, 0]$.




Fig. 2. Plots of $x = x_0 + x_1$ and $y = y_0 + y_1$ for $[\omega_1, \omega_2, \tau, \alpha_1, \alpha_2, \epsilon, x(0), \dot{x}(0), y(0), \dot{y}(0)] = [1, 0.1, 0.1, 0.2, 3, 1, 0, 1, 0]$.

Figures 1-3 show the plots of approximate values for x and y for different values of parameters of system (1) and different initial values of x and y .

IV. CONCLUSIONS

In this paper, we studied the dynamics of a system of two van der Pol oscillators with delayed position and velocity. We obtained approximate values for frequencies of the system. On account of, He's parameter-expansion method is an efficient




Fig. 3. Plots of $x = x_0 + x_1$ and $y = y_0 + y_1$ for $[\omega_1, \omega_2, \tau, \alpha_1, \alpha_2, \epsilon, x(0), \dot{x}(0), y(0), \dot{y}(0)] = [1, 0.01, 0.4, 0.5, 5, 0.1, 0.26, 0.1, 0.26]$.

method to solve such systems. The procedure of looking for a solution is also very simple and straightforward.

REFERENCES

- [1] J.H. He, *Variational iteration method—a kind of non-linear analytical technique: some examples*, Int. J. Non-linear Mech. 34(4) (1999) 699–708.
- [2] M.T. Darvishi, F. Khani, A.A. Soliman, *The numerical simulation for stiff systems of ordinary differential equations*, Comput. Math. Appl. 54(7-8) (2007) 1055–1063.
- [3] M.T. Darvishi, F. Khani, *Numerical and explicit solutions of the fifth-order Korteweg-de Vries equations*, Chaos, Solitons and Fractals 39 (2009) 2484–2490.
- [4] S. Abbasbandy, M.T. Darvishi, *A numerical solution of Burgers' equation by modified Adomian method*, Appl. Math. Comput. 163 (2005) 1265–1272.
- [5] S. Abbasbandy, M.T. Darvishi, *A numerical solution of Burgers' equation by time discretization of Adomian's decomposition method*, Appl. Math. Comput. 170 (2005) 95–102.
- [6] J.H. He, *New interpretation of homotopy perturbation method*, Int. J. Mod. Phys. B 20(18) (2006) 2561–2568.
- [7] J.H. He, *Application of homotopy perturbation method to nonlinear wave equations*, Chaos, Solitons and Fractals 26(3) (2005) 695–700.
- [8] J.H. He, *Homotopy perturbation method for bifurcation of nonlinear problems*, Int. J. Nonlinear Sci. Numer. Simul. 6(2) (2005) 207–208.
- [9] M.T. Darvishi, F. Khani, *Application of He's homotopy perturbation method to stiff systems of ordinary differential equations*, Zeitschrift fur Naturforschung A, 63a (1-2) (2008) 19–23.
- [10] M.T. Darvishi, F. Khani, S. Hamed-Nezhad, S.-W. Ryu, *New modification of the HPM for numerical solutions of the sine-Gordon and coupled sine-Gordon equations*, Int. J. Comput. Math. 87(4) (2010) 908–919.
- [11] M.T. Darvishi, *Preconditioning and domain decomposition schemes to solve PDEs*, Int'l J. of Pure and Applied Math. 1(4) (2004) 419–439.
- [12] M.T. Darvishi, S. Kheybari, F. Khani, *A numerical solution of the Korteweg-de Vries equation by pseudospectral method using Darvishi's preconditionings*, Appl. Math. Comput. 182(1) (2006) 98–105.
- [13] M.T. Darvishi, M. Javidi, *A numerical solution of Burgers' equation by pseudospectral method and Darvishi's preconditioning*, Appl. Math. Comput. 173(1) (2006) 421–429.
- [14] M.T. Darvishi, F. Khani, S. Kheybari, *Spectral collocation solution of a generalized Hirota-Satsuma KdV equation*, Int. J. Comput. Math. 84(4) (2007) 541–551.
- [15] M.T. Darvishi, F. Khani, S. Kheybari, *Spectral collocation method and Darvishi's preconditionings to solve the generalized Burgers-Huxley equation*, Commun. Nonlinear Sci. Numer. Simul. 13(10) (2008) 2091–2103.
- [16] S.J. Liao, *An explicit, totally analytic approximate solution for Blasius viscous flow problems*, Int. J. Non-Linear Mech. 34 (1999) 759–778.
- [17] S.J. Liao, *Beyond perturbation: introduction to the homotopy analysis method*, Chapman & Hall/CRC Press, Boca Raton, 2003.
- [18] S.J. Liao, *On the homotopy analysis method for nonlinear problems*, Appl. Math. Comput. 147 (2004) 499–513.
- [19] S.J. Liao, *A new branch of solutions of boundary-layer flows over an impermeable stretched plate*, Int. J. Heat Mass Transfer 48 (2005) 2529–2539.
- [20] S.J. Liao, *A general approach to get series solution of non-similarity boundary-layer flows*, Commun. Nonlinear Sci. Numer. Simul. 14(5) (2009) 2144–2159.
- [21] M.T. Darvishi, F. Khani, *A series solution of the foam drainage equation*, Comput. Math. Appl. 58 (2009) 360–368.
- [22] A. Aziz, F. Khani, M.T. Darvishi, *Homotopy analysis method for variable thermal conductivity heat flux gage with edge contact resistance*, Zeitschrift fuer Naturforschung A, 65a(10) (2010) 771–776.
- [23] J.H. He, M.A. Abdou, *New periodic solutions for nonlinear evolution equations using Exp-function method*, Chaos, Solitons and Fractals 34 (2007) 1421–1429.
- [24] J.H. He, X.H. Wu, *Exp-function method for nonlinear wave equations*, Chaos, Solitons and Fractals 30(3) (2006) 700–708.
- [25] J.H. He, X.H. Wu, *Construction of solitary solution and compacton-like solution by variational iteration method*, Chaos, Solitons and Fractals 29 (2006) 108–113.
- [26] F. Khani, S. Hamed-Nezhad, M.T. Darvishi, S.-W. Ryu, *New solitary wave and periodic solutions of the foam drainage equation using the Exp-function method*, Nonlin. Anal.: Real World Appl. 10 (2009) 1904–1911.

- [27] B.-C. Shin, M.T. Darvishi, A. Barati, *Some exact and new solutions of the Nizhnik-Novikov-Vesselov equation using the Exp-function method*, Comput. Math. Appl. 58(11/12) (2009) 2147–2151.
- [28] X.H. Wu, J.H. He, *Exp-function method and its application to nonlinear equations*, Chaos, Solitons and Fractals 38(3) (2008) 903–910.
- [29] X. Li., J.C. Ji, C.H. Hansen, *Dynamics of two delay coupled van der Pol oscillators*, Mechanics Research Communications 33 (2006) 614–627.
- [30] J.H. He, *Bookkeeping parameter in perturbation methods*, Int. J. Nonlinear Sci. Numer. Simul. 2 (2001) 257–264.
- [31] M.T. Darvishi, A. Karami, B.-C. Shin, *Application of He's parameter-expansion method for oscillators with smooth odd nonlinearities*, Phys. Lett. A 372(33) (2008) 5381–5384.
- [32] B.-C. Shin, M.T. Darvishi, A. Karami, *Application of He's parameter-expansion method to a nonlinear self-excited oscillator system*, Int. J. Nonlin. Sci. Num. Simulation 10(1) (2009) 137–143.
- [33] S.T. Mohyud-Din, M.A. Noor, K.I. Noor, *Parameter-expansion techniques for strongly nonlinear oscillators*, Int. J. Nonlin. Sci. Num. Simulation 10(5) (2009) 581–583.
- [34] N.H. Sweilam, R.F. Al-Bar, *Implementation of the parameter-expansion method for the coupled van der Pol oscillators*, Int. J. Nonlin. Sci. Num. Simulation 10(2) (2009) 259–264.
- [35] N.H. Sweilam, M.M. Khader, *Application of He's parameter-expansion method for the nonlinear differential equations*, Int. J. Nonlin. Sci. Num. Simulation 10(2) (2009) 265–272.
- [36] F.O. Zengin, M.O. Kaya, S.A. Demirbag, *Application of parameter-expansion method to nonlinear oscillators with discontinuities*, Int. J. Nonlin. Sci. Num. Simulation 9(3) (2008) 267–270.
- [37] L. Xu, *He's parameter-expanding methods for strongly nonlinear oscillators*, J. Comput. Appl. Math. 207(1) (2007) 148–154.
- [38] L. Xu, *Application of He's parameter-expansion method to an oscillation of a mass attached to a stretched elastic wire*, Phys. Lett. A 368(3-4) (2007) 259–262.
- [39] L. Xu, *Determination of limit cycle by He's parameter-expanding method for strongly nonlinear oscillators*, J. of Sound and Vibration 302(1-2) (2007) 178–184.
- [40] L.N. Zhang, L. Xu, *Determination of the limit cycle by He's parameter-expansion for oscillators in a $u(3)/(1+u(2))$ potential*, Zeitschrift fur Naturforschung Section A 62(7-8) (2007) 396–398.