# Exponential State Estimation for Neural Networks with Leakage, Discrete and Distributed Delays

Liyuan Wang, Shouming Zhong

Abstract—In this paper, the design problem of state estimator for neural networks with the mixed time-varying delays are investigated by constructing appropriate Lyapunov-Krasovskii functionals and using some effective mathematical techniques. In order to derive several conditions to guarantee the estimation error systems to be globally exponential stable, we transform the considered systems into the neural-type time-delay systems. Then with a set of linear inequalities(LMIs), we can obtain the stable criteria. Finally, three numerical examples are given to show the effectiveness and less conservatism of the proposed criterion.

*Keywords*—State estimator, Neural networks, Globally exponential stability.

# I. INTRODUCTION

I N the past decades, we can easily find that neural networks have been applied in many fields such as signal processing, pattern recognition and static image processing. And the applications that introduced above strongly depend on the dynamic behavior of the network. For a long time, many investigator pay same attentions on the stability of delayed neural networks, in [1-3], the authors discussed the recurrent neural networks, the delayed stochastic genetic regulatory networks and the uncertain fuzzy system. Therefore, because of the finite switching speed of amplifiers or the finite signal propagation time, neural networks often has time delays so many sufficient conditions have been proposed for verifying the globally asymptotically stable and globally exponential stability of the neural networks [4-10] and [23,24].

In recent years, the state estimation problems of the neural networks have been obtained large amount of attention from [11-21], [25] discussed the problem of state estimation of neural networks with the leakage delays, discrete time-varying delays and distributed time-varying delays. By using convex combination technique and some analysis techniques, some stability criteria for the existence of the state estimator are derived. [30] provided some sufficient conditions for the system to be globally asymptotically stable and exponentially stable, respectively. such conditions could be easily checked by utilizing the recently developed interior-point methods and

This work was supported by the National Basic Research Program of China(2010CB732501) and the National Nature Science Foundation of the China(61273015).

Liyuan Wang and Shouming Zhong are with the School of Mathematics Science, University Electronic Science and Technology of China, Chengdu 611731, PR China.

Shouming Zhong is with Key Laboratory for NeuroInformation of Ministry of Education, University of Electronic Science and Technology of China, Chengdu 611731, PR China.

(e-mail :wangliyuan610@126.com).

they are expressed in the form of LMIs. and not having the tuning of parameters needed in [31]. And the author of [22] used the delay departing technique to discuss the problem of the stability criteria of neural networks with the distributed time-varying delays, and it has derived the less conservation criterion to deal with the analysis problem of globally exponential stability for neural networks.

In this paper, the problem of state estimation of neural networks with leakage delays, discrete time-varying delays and distributed delays is investigated. By constructing a new class of Lyapunov function and using the delay departing technique, convex combination technique and some analysis techniques, the problem of estimating the neural states via available output measurements such that the estimation error converges to zero exponentially is investigated. bucause the system we discuss included the leakage delay, so at last we discussed the upper bounds of some variable. Note that the LMIs method can obtained less conservative criterion when deal with the analysis problem of globally exponential stability for neural networks, two numerical examples are given to illustrate the effectiveness of the propose methods.

Notation: Throughout this paper,  $\mathbb{R}^n$  denote the ndimensional Euclidean space and the set of all  $n \times m$  real matrices are denoted by  $\mathbb{R}^{n \times m}$ . And when X and Y are symmetric matrices, the notation  $X \ge Y$  means that X - Yis positive. The superscript T denotes transposition of matrix.  $\|\cdot\|$  and \* denote the Euclidean norm and the symmetric block, respectively,  $diag\{\cdots\}$  is a block diagonal matrix.  $\lambda_{min}$ and  $\lambda_{max}$  stand for the smallest and largest eigenvalue of a given matrix, respectively.

#### **II. PROBLEM STATEMENT**

Consider the following neural networks with mixed timevarying delays:

$$\dot{x}(t) = -Ax(t-\sigma) + B_1g(x(t)) + B_2g(x(t-\tau(t))) + \tilde{E}\int_{t-r(t)}^t g(x(s))ds + I,$$
(1)

$$y(t) = Cx(t) + Df(t, x(t))$$

where  $x(\cdot) = [x_1(\cdot), x_2(\cdot), \cdots, x_n(\cdot)]^T \in \mathbb{R}^n$  is neural state vector;  $y(\cdot) \in \mathbb{R}^m$  is the output of the networks;  $A = diag\{a_1, \cdots, a_n\} > 0$  is a diagonal matrix with positive entries  $a_i > 0$ ; the matrices  $B_1, B_2$  and  $\tilde{E}$  represent the connection weight matrix, the discretely delayed connection weight matrix, and distributively delayed connection weight matrix, respectively; the matrices  $C \in \mathbb{R}^{m \times n}$ 

and  $D \in \mathbb{R}^{m \times n}$  are the output weighting matrices;  $g(x(\cdot)) = [g_1(x_1(\cdot)), g_1(x_2(\cdot)), \cdots, g_1(x_n(\cdot))]^T, g \in \mathbb{R}^m$ denotes the neural activation function;  $I = [I_1, \cdots, I_n]^T$  is an external input vector,  $\sigma$  is the leakage delay and  $\sigma > 0$ , the discrete time-varying delays and the distributed time-varying delays are denoted by  $\tau(t)$  and r(t), respectively, and they satisfy

$$0 < d_1 \le \tau(t) \le d_2, 0 < r(t) \le \bar{r}, \dot{\tau}(t) \le \mu$$
 (\*)

in above inequality  $d_1, d_2, \bar{r}$  and  $\mu$  are constants; and  $f: R \times R^n \longrightarrow R^n$  represent the neural-dependent nonlinear disturbances. Nest, we design the full-order state estimation for the neural networks (1) as the following:

$$\dot{\bar{x}}(t) = -A\bar{x}(t-\sigma) + B_1g(\bar{x}(t)) + B_2g(\bar{x}(t-\tau(t))) + \tilde{E}\int_{t-r(t)}^t g(\bar{x}(s))ds + I + K(y-\bar{y})$$
(2)  
$$\bar{y}(t) = C\bar{x}(t) + Df(t,\bar{x}(t)),$$

where  $\bar{x}(t)$  and  $\bar{y}(t)$  represent the estimation of the neuron state and the estimated output vector, respectively, and  $K \in \mathbb{R}^{n \times m}$  is the gain matrix of the estimator to be designed later. when the error vector is defined as  $\varepsilon(t) = x(t) - \bar{x}(t)$ , we can directly obtained the error dynamics from (1) and (2):

$$\begin{split} \dot{\varepsilon}(t) &= -A\varepsilon(t-\sigma) - KC\varepsilon(t) + B_1\varphi(t) + B_2\varphi(t-\tau(t)) \\ &+ \tilde{E} \int_{t-r(t)}^t \varphi(s)ds - KD\psi(t) \end{split}$$
(3)

where  $\varphi(t) = g(x(t)) - g(\bar{x}(t)), \psi(t) = f(t, x(t)) - f(t, \bar{x}(t)),$ then the above system can be translated into the following equivalent form when the error vector is defined as  $\varepsilon(t) = x(t) - \bar{x}(t)$ :

$$\frac{d}{dt}[\varepsilon(t) - A \int_{t-\sigma}^{t} \varepsilon(s)ds] = -(A + KC)\varepsilon(t) + B_{1}\varphi(t) + B_{2}\varphi(t-\tau(t)) + \tilde{E} \int_{t-r(t)}^{t} \varphi(s)ds - KD\psi(t)$$
(4)

(3)and(4) satisfy  $\varepsilon(t) = \Phi(t), t \in [-\tau, 0]$ , and  $\tau = max\{d_2, \overline{r}\}\$ g and f satisfy the following Assumption.

Assumption (A): The neuron activation function  $g(\cdot)$  in (1) is bounded and satisfy the following two constant matrices  $\varphi^- = diag\{\phi_1^-, \phi_2^-, \cdots, \phi_n^-\}, \varphi^+ = diag\{\phi_1^+, \phi_2^+, \cdots, \phi_n^+\}$ , such that:

$$\phi_l^- \le \frac{g_l(\alpha) - g_l(\beta)}{\alpha - \beta} \le \phi_l^+ \tag{5}$$

for all  $\alpha, \beta \in R, \alpha \neq \beta, l = 1, 2, \cdots, n$ 

Assumption (B): The neuron-dependent nonlinear disturbances f in (1) is bounded and there are a positive diagonal matrices  $\hat{W}$  and two constant matrices  $\omega^- = diag\{\omega_1^-, \omega_2^-, \cdots, \omega_n^-\}, \omega^+ = diag\{\omega_1^+, \omega_2^+, \omega_n^+\}$ , such that the following inequality:

$$[f(t, x(t)) - f(t, \bar{x}(t)) - \omega^{-}(x(t) - \bar{x}(t))]^{T} \hat{W} \times [\omega^{+}(x(t) - \bar{x}(t)) - (f(t, x(t)) - f(t, \bar{x}(t)))] \ge 0$$
(6)

In order to obtain our results, we will introduce some lemmas. **Definition 1**. The equilibrium point 0 of system (3) is said to be globally exponentially stable, if there exist scalars k > 0 and  $\delta > 0$  such that:

$$\|\varepsilon(t)\| \le \kappa \sup_{-\tau \le s \le 0} \|\Phi(s)\| e^{-\delta t}, \forall t > 0,$$

**Lemma 1** (Schur complement). For a given symmetric matrix  $S = S^T = \begin{bmatrix} S_{11} & S_{12} \\ * & S_{22} \end{bmatrix}$ , where  $S_{11} \in \mathbb{R}^{k \times k}$ , the following conditions are equivalent:

$$\begin{aligned} (1)S &< 0;\\ (2)S_{11} &< 0, S_{22} - S_{12}^T S_{11}^{-1} S_{12} &< 0;\\ (3)S_{22} &< 0, S_{11} - S_{12} S_{22}^{-1} S_{12}^T &< 0; \end{aligned}$$

**Lemma 2** [9]. For any constant matrix  $Z \in \mathbb{R}^{n \times n}$ ,  $Z = Z^T > 0$ , scalars  $h_2 > h_1 > 0$ , such that the following integrations are well defined, then:

$$- (h_2 - h_1) \int_{t-h_2}^{t-h_1} x^T(s) Zx(s) ds$$

$$\leq - \int_{t-h_2}^{t-h_1} x^T(s) ds Z \int_{t-h_2}^{t-h_1} x(s) ds$$

$$- \frac{1}{2} (h_2^2 - h_1^2) \int_{-h_2}^{-h_1} \int_{t+\theta}^t x^T(s) Zx(s) ds d\theta$$

$$\leq \int_{-h_2}^{-h_1} \int_{t+\theta}^t x^T(s) ds d\theta Z \int_{-h_2}^{-h_1} \int_{t+\theta}^t x(s) ds d\theta$$

**Lemma 3** [10]. For any scalar  $h(t) \ge 0$  and any constant matrix  $Q \in \mathbb{R}^{n \times n}, Q = Q^T > 0$ , the following inequalities hold:

$$\begin{split} &-\int_{t-h(t)}^{t} \dot{x}^{T}(s) Q \dot{x}(s) ds \leq h(t) \zeta(t) \chi Q^{-1} \chi^{T} \zeta(t) + 2 \zeta^{T}(t) \\ &\times [x(t) - x(t-h(t)], \\ \text{where } \zeta^{T}(t) = [x^{T}(t) \quad x^{T}(t-h(t)) \quad x^{T}(t-\frac{h_{u}}{2}) \quad x^{T}(t-\frac{h_{u}}{2}) \end{split}$$

 $h_u$ )  $\dot{x}^T(t) p(t)$ ],

and  $\chi$  is free weighting matrix with appropriate dimensions.

## III. STABILITY ANALYSIS

In this section we will give sufficient conditions under which the system (3) or (4) is globally asymptotically stable. Firstly, the following notations are introduced for the representation convenience:

$$L_{1} = diag\{\phi_{1}^{-}\phi_{1}^{+}, \phi_{2}^{-}\phi_{2}^{+}, \cdots, \phi_{n}^{-}\phi_{n}^{+}\},\$$

$$L_{2} = diag\{\frac{\phi_{1}^{-}+\phi_{1}^{+}}{2}, \frac{\phi_{2}^{-}+\phi_{2}^{+}}{2}, \frac{\phi_{n}^{-}+\phi_{n}^{+}}{2}\}.$$

From the above Assumption (A), we can obtain the following inequalities:

$$[\varphi_l(t) - \phi_l^- e_l(t)]^T [\varphi_l(t) - \phi_l^+ e_l(t)] \le 0, l = 1, 2, \cdots, n,$$

**Theorem 1** For given scalars  $d_1, d_2, \sigma, \bar{r}$  and  $\mu$  satisfy (\*) and Assumption (A) and (B) hold, then the system (3) or (4) is globally exponentially stable with the rate index k if there exist P > 0,  $R_l > 0$ , (l = 1, 2, 3, 4, 5, 6),  $Q_m > 0$ , (m = 1, 2, 3, 4, 5, 6, 7, 8),  $T_n > 0$ , (n = 1, 2, 3), any matrices  $G, U_k, V_k, W_k, X_k, Y_k, Z_k, S_k (k = 1, 2)$ , and diagonal matrices  $\hat{U} > 0, \hat{V} > 0, \hat{W} > 0$  such that the following LMIs hold according to (7) and (8), then one can obtain

$$E_{16\times16} + d_1 e^{-2kd_1} U Q_6^{-1} U^T + (d^* - d_1) e^{-2kd^*} V \times Q_7^{-1} V^T + (d_2 - d^*) e^{-2kd_2} X Q_8^{-1} X^T < 0$$
(7)

$$E_{16\times16} + d_1 e^{-2kd_1} U Q_6^{-1} U^T + (d^* - d_1) e^{-2kd^*} W \times Q_7^{-1} W^T + (d_2 - d^*) e^{-2kd_2} X Q_8^{-1} X^T < 0$$
(8)

$$F_{16\times 16} + d_1 e^{-2kd_1} U Q_6^{-1} U^T + (d^* - d_1) e^{-2kd^*} S \times Q_7^{-1} S^T + (d_2 - d^*) e^{-2kd_2} Y Q_8^{-1} Y^T < 0,$$
(9)

$$F_{16\times 16} + d_1 e^{-2kd_1} U Q_6^{-1} U^T + (d^* - d_1) e^{-2kd^*} S \times Q_7^{-1} S^T + (d_2 - d^*) e^{-2kd_2} Z Q_8^{-1} Z^T < 0,$$
(10)

# where

and

$$\begin{split} E_{1,1} &= 2kP - PA - A^TP - GC - C^TG^T + R_1 + R_2 \\ &+ R_3 + R_4 + R_6 + \sigma^2 Q_1 + d_1 Q_3 + (d^* - d_1)Q_4 + (d_2 \\ &- d^*)Q_5 - 2e^{-2kd_1}T_1 - 2\frac{d^* - d_1}{d^* + d_1}e^{-2kd^*}T_2 - L_1\hat{U} \\ &- L_3\hat{W} + e^{-2kd_1}U_1 + e^{-2kd_1}U_1^T - 2\frac{d_2 - d^*}{d_2 + d^*}e^{-2kd_2}T_3, \\ E_{1,3} &= e^{-2kd_1}(-U_1 + U_2^T), E_{1,7} = -C^TG^T, \\ E_{1,8} &= PB_1 + L_2\hat{U}, E_{1,9} = PB_2, E_{1,10} = -GD + L_4\hat{W} \\ E_{1,11} &= -2kPA + A^TPA + C^TG^TA, E_{1,12} = \frac{2}{d_1}e^{-2kd_1}T_1 \\ E_{1,13} &= P\tilde{E}, E_{1,14} = \frac{2}{d^* + d_1}e^{-2kd^*}T_2, \\ E_{1,15} &= \frac{2}{d^* + d_1}e^{-2kd^*}T_2, E_{1,16} = \frac{2}{d_2 + d^*}e^{-2kd_2}T_3, \\ E_{2,2} &= -e^{-2k\sigma}R_6, E_{2,7} = -A^TP, \\ E_{3,3} &= e^{-2kd_1}(U_2^T + U_2) - e^{-2kd_1}R_2 + e^{-2kd^*}(W_1 + W_1^T), \\ E_{3,6} &= e^{-2kd^*}(-W_1 + W_2^T) \\ E_{4,4} &= -e^{-2kd^*}R_4 + e^{-2kd^*}(-V_1 - V_1^T) + e^{-2kd_2}(X_1 + X_1^T), \\ E_{4,5} &= -e^{-2kd_2}(-X_1 + X_2^T), E_{4,6} = -e^{-2kd^*}(V_1 - V_2^T), \\ E_{5,5} &= -e^{-2kd_2}R_3 + e^{-2kd_2}(-X_2 - X_2^T), \\ E_{6,6} &= -L_1\hat{V} - (1 - \mu)e^{-2kd^*}R_1 + e^{-2kd^*}(V_2 + V_2^T) \\ &+ e^{-2kd^*}(-W_2 - W_2^T), \end{split}$$

$$\begin{split} &E_{6,9} = L_2 \hat{V}, \\ &E_{7,7} = -2P + d_1 Q_6 + \frac{d_1^2}{2} T_1 + \frac{d^{*2} - d_1^2}{2} T_2 + \frac{d_2^2 - d^{*2}}{2} T_3 \\ &+ (d^* - d_1) Q_7 + (d_2 - d^*) Q_8, \\ &E_{7,8} = PB_1, \quad E_{7,9} = PB_2, \quad E_{7,10} = -GD, \\ &E_{7,13} = P\tilde{E}, E_{8,8} = R_5 + \bar{r}^2 Q_2 - \hat{U}, E_{8,11} = -B_1^T PA, \\ &E_{9,9} = -(1 - \mu) e^{-2kd^*} R_5 - \hat{V}, \quad E_{9,11} = -B_2^T PA, \\ &E_{10,10} = -\hat{W}, \quad E_{10,11} = D^T G^T A, \\ &E_{11,11} = 2kA^T PA - e^{-2k\sigma} Q_1, \quad E_{11,13} = -A^T P\tilde{E}, \\ &E_{12,12} = -\frac{1}{d_1} e^{-2kd_1} Q_3 - \frac{2}{d_1^2} e^{-2kd_1} T_1, E_{13,13} = -e^{-2k\bar{r}} Q_2, \\ &E_{14,14} = -\frac{1}{d^* - d_1} e^{-2kd^*} Q_4 - \frac{2}{d^{*2} - d_1^2} e^{-2kd^*} T_2, \\ &E_{14,15} = -\frac{2}{d^{*2} - d_1^2} e^{-2kd^*} T_2, \\ &E_{16,16} = -\frac{1}{d_2 - d^*} e^{-2kd_2} Q_5 - \frac{2}{d_2^2 - d^{*2}} e^{-2kd_2} T_3 \\ &F_{1,15} = \frac{2}{d_2 + d^*} e^{-2kd_2} T_3, \\ &F_{3,3} = e^{-2kd_1} R_2 + e^{-2kd_1} (-U_2 - U_2^T) + e^{-2kd^*} (S_1 + S_1^T), \\ &F_{3,4} = e^{-2kd^*} (-S_1 + S_2^T), \quad F_{3,6} = 0, \\ &F_{4,4} = e^{-2kd^*} R_4 + e^{-2kd^*} (-S_2 - S_2^T) + e^{-2kd_2} (Y_1 + Y_1^T), \\ &F_{4,5} = 0, \quad F_{4,6} = e^{-2kd_2} (Y_1 + Y_2^T), \\ &F_{5,6} = e^{-2kd_2} (Z_1 - Z_2^T), \\ &F_{6,6} = -(1 - \mu) e^{-2kd_2} R_1 + e^{-2kd_2} (-Y_2 - Y_2^T) \\ &+ e^{-2kd_2} (Z_2 + Z_2^T), \\ &F_{9,9} = -(1 - \mu) e^{-2kd_2} R_5 - \hat{V}, \\ &F_{15,15} = -\frac{1}{d_2 - d^*} e^{-2kd_2} Q_5 - \frac{2}{d_2^2 - d^{*2}} e^{-2kd_2} T_3, \\ &F_{15,16} = -\frac{2}{d_2^2 - d^{*2}} e^{-2kd_2} T_3, \\ &F_{15,16} = -\frac{2}{d_2^2 - d^{*2}} e^{-2kd_2} R_3, \\ &F_{15,16} = -\frac{2}{d_2^2 - d^{*2}} e^{-2kd_2} R_3, \\ &F_{16,16} = -\frac{1}{d_2 - d^*} e^{-2kd_2} Q_5 - \frac{2}{d_2^2 - d^{*2}} e^{-2kd_2} T_3, \\ &F_{16,16} = -\frac{1}{d_2 - d^*} e^{-2kd_2} Q_5 - \frac{2}{d_2^2 - d^{*2}} e^{-2kd_2} T_3, \\ &F_{16,16} = -\frac{1}{d_2 - d^*} e^{-2kd_2} Q_5 - \frac{2}{d_2^2 - d^{*2}} e^{-2kd_2} T_3, \\ &F_{16,16} = -\frac{1}{d_2 - d^*} e^{-2kd_2} Q_5 - \frac{2}{d_2^2 - d^{*2}} e^{-2kd_2} T_3, \\ &F_{16,16} = -\frac{1}{d_2 - d^*} e^{-2kd_2} Q_5 - \frac{2}{d_2^2 - d^{*2}} e^{-2kd_2} T_3, \\ &F_{16,16} = -\frac{1}{d_2 - d^*} e^{-2kd_2} Q_5 - \frac{2}{d_2^2 - d^$$

the other entries of E is 0 and the other entries of F is the same as E, and  $d^* \in (d_1, d_2), d^* = \lambda d_1 + (1 - \lambda)d_2, \lambda \in (0, 1)$ , The gain matrix of state estimator is given by

$$K = P^{-1}G \tag{11}$$

*Proof:* Consider a novel augmented of Lyapunov-Krasovskii functional for the system (3) or (4) as follows:

$$V(t) = V_1(t) + V_2(t) + V_3(t) + V_4(t),$$
(12)

where

$$V_1(t) = e^{2kt} [\varepsilon(t) - A \int_{t-\sigma}^t \varepsilon(s) ds]^T P[\varepsilon(t) - A \int_{t-\sigma}^t \varepsilon(s) ds],$$

#### ISNI:000000091950263

$$V_{2}(t) = \int_{t-\tau(t)}^{t} e^{2ks} \varepsilon^{T}(s) R_{1}\varepsilon(s) ds$$
  
+  $\int_{t-d_{1}}^{t} e^{2ks} \varepsilon^{T}(s) R_{2}\varepsilon(s) ds$   
+  $\int_{t-d_{2}}^{t} e^{2ks} \varepsilon^{T}(s) R_{3}\varepsilon(s) ds$   
+  $\int_{t-d^{*}}^{t} e^{2ks} \varepsilon^{T}(s) R_{4}\varepsilon(s) ds$   
+  $\int_{t-\tau(t)}^{t} e^{2ks} \varphi^{T}(s) R_{5}\varphi(s) ds$   
+  $\int_{t-\sigma}^{t} e^{2ks} \varepsilon^{T}(s) R_{6}\varepsilon(s) ds,$ 

$$\begin{split} V_{3}(t) = & \sigma \int_{-\sigma}^{0} \int_{t+\theta}^{t} e^{2ks} \varepsilon^{T}(s) Q_{1}\varepsilon(s) ds d\theta \\ & + \bar{r} \int_{-\bar{r}}^{0} \int_{t+\theta}^{t} e^{2ks} \varphi^{T}(s) Q_{2}\varphi(s) ds d\theta \\ & + \int_{-d_{1}}^{0} \int_{t+\theta}^{t} e^{2ks} \varepsilon^{T}(s) Q_{3}\varepsilon(s) ds d\theta \\ & + \int_{-d^{*}}^{-d_{1}} \int_{t+\theta}^{t} e^{2ks} \varepsilon^{T}(s) Q_{4}\varepsilon(s) ds d\theta \\ & + \int_{-d_{2}}^{-d^{*}} \int_{t+\theta}^{t} e^{2ks} \varepsilon^{T}(s) Q_{5}\varepsilon(s) ds d\theta \\ & + \int_{-d_{1}}^{0} \int_{t+\theta}^{t} e^{2ks} \dot{\varepsilon}^{T}(s) Q_{6}\dot{\varepsilon}(s) ds d\theta \\ & + \int_{-d^{*}}^{-d^{*}} \int_{t+\theta}^{t} e^{2ks} \dot{\varepsilon}^{T}(s) Q_{6}\dot{\varepsilon}(s) ds d\theta \\ & + \int_{-d^{*}}^{-d^{*}} \int_{t+\theta}^{t} e^{2ks} \dot{\varepsilon}^{T}(s) Q_{7}\dot{\varepsilon}(s) ds d\theta \\ & + \int_{-d_{2}}^{-d^{*}} \int_{t+\theta}^{t} e^{2ks} \dot{\varepsilon}^{T}(s) Q_{8}\dot{\varepsilon}(s) ds d\theta \end{split}$$

$$\begin{aligned} V_4(t) &= \int_{t-d_1}^t \int_{\theta}^t \int_{\lambda}^t e^{2ks} \dot{\varepsilon}^T(s) T_1 \dot{\varepsilon}(s) ds d\lambda d\theta \\ &+ \int_{t-d^*}^{t-d_1} \int_{\theta}^t \int_{\lambda}^t e^{2ks} \dot{\varepsilon}^T(s) T_2 \dot{\varepsilon}(s) ds d\lambda d\theta \\ &+ \int_{t-d_2}^{t-d^*} \int_{\theta}^t \int_{\lambda}^t e^{2ks} \dot{\varepsilon}^T(s) T_3 \dot{\varepsilon}(s) ds d\lambda d\theta, \end{aligned}$$

The derivative of V(t) with respect to time along the trajectory  $\left(1\right)$  is

$$\dot{V}(t) = \dot{V}_1(t) + \dot{V}_2(t) + \dot{V}_3(t) + \dot{V}_4(t),$$
(13)

The time derivative of  $V_i(t), i = 1, 2, 3, 4$ , is obtained as

$$\dot{V}_{1}(t) = 2ke^{2kt}[\varepsilon(t) - A\int_{t-\sigma}^{t} \varepsilon(s)ds]^{T}P[\varepsilon(t) - A\int_{t-\sigma}^{t} \varepsilon(s)ds] + 2e^{2kt}[\varepsilon(t) - A\int_{t-\sigma}^{t} \varepsilon(s)ds]^{T} \times P[-(A + KC)\varepsilon(t) + B_{1}\varphi(t) + B_{2}\varphi(t - \tau(t)) + E\int_{t-r(t)}^{t} \varphi(s)ds - KD\psi(t)],$$
(14)

$$\dot{V}_{2}(t) \leq e^{2kt}\varepsilon^{T}(t)R_{1}\varepsilon(t) - (1-\mu)e^{2k(t-\tau(t))}\varepsilon^{T}(t-\tau(t))$$

$$\times R_{1}\varepsilon(t-\tau(t)) + e^{2kt}\varepsilon^{T}(t)R_{2}\varepsilon(t) - e^{2k(t-d_{1})}$$

$$\times \varepsilon^{T}(t-d_{1})R_{2}\varepsilon(t-d_{1}) + e^{2kt}\varepsilon^{T}(t)R_{3}\varepsilon(t)$$

$$- e^{2k(t-d_{2})}\varepsilon^{T}(t-d_{2})R_{3}\varepsilon(t-d_{2}) + e^{2kt}\varepsilon^{T}(t)R_{4}$$

$$\times \varepsilon(t) - e^{2k(t-d^{*})}\varepsilon^{T}(t-d^{*})R_{4}\varepsilon(t-d^{*}) + e^{2kt}$$

$$\times \varphi^{T}(t)R_{5}\varphi(t) - (1-\mu)e^{2k(t-\tau(t))}\varphi^{T}(t-\tau(t))$$

$$\times R_{5}\varphi^{T}(t-\tau(t)) + e^{2kt}\varepsilon^{T}(t)R_{6}\varepsilon(t) - e^{2k(t-\sigma)}$$

$$\times \varepsilon^{T}(t-\sigma)R_{6}\varepsilon(t-\sigma)$$
(15)

$$\begin{split} \dot{V}_{3}(t) &\leq e^{2kt} \varepsilon^{T}(t) [\sigma^{2}Q_{1} + d_{1}Q_{3} + (d^{*} - d_{1})Q_{4} \\ &+ (d_{2} - d^{*})Q_{5}]\varepsilon(t) + \bar{r}^{2}e^{2kt}\varphi^{T}(t)Q_{2}\varphi(t) \\ &+ e^{2kt}\dot{\varepsilon}^{T}(t) [d_{1}Q_{6} + (d^{*} - d_{1})Q_{7} + (d_{2} - d^{*}) \\ &\times Q_{8}]\dot{\varepsilon}(t) - \sigma e^{2k(t - \sigma)} \int_{t - \sigma}^{t} \varepsilon^{T}(s)Q_{1}\varepsilon(s)ds \\ &- r(t)e^{2k(t - \bar{r})} \int_{t - r(t)}^{t} \varphi^{T}(s)Q_{2}\varphi(s)ds \\ &- e^{2k(t - d_{1})} \int_{t - d_{1}}^{t} \varepsilon^{T}(s)dsQ_{3}\varepsilon(s)ds - e^{2k(t - d^{*})} \\ &\times \int_{t - d^{*}}^{t - d_{1}} \varepsilon^{T}(s)Q_{4}\varepsilon(s)ds - e^{2k(t - d_{2})} \int_{t - d_{2}}^{t - d^{*}} \varepsilon^{T}(s) \\ &\times Q_{5}\varepsilon(s)ds - e^{2k(t - d_{1})} \int_{t - d_{1}}^{t} \dot{\varepsilon}^{T}(s)Q_{6}\dot{\varepsilon}(s)ds \\ &- e^{2k(t - d^{*})} \int_{t - d^{*}}^{t - d_{1}} \dot{\varepsilon}^{T}(s)Q_{7}\dot{\varepsilon}(s)ds - e^{2k(t - d_{2})} \\ &\times \int_{t - d^{*}}^{t - d^{*}} \dot{\varepsilon}^{T}(s)Q_{8}\dot{\varepsilon}(s)ds, \end{split}$$

$$(16)$$

$$\dot{V}_{4}(t) \leq e^{2kt}\dot{\varepsilon}^{T}(s) \left[\frac{d_{1}^{2}}{2}T_{1} + \frac{d^{*2} - d_{1}^{2}}{2}T_{2} + \frac{d_{2}^{2} - d^{*2}}{2}T_{3}\right]\dot{\varepsilon}(t) - e^{2k(t-d_{1})} \int_{t-d_{1}}^{t} \int_{\lambda}^{t} \dot{\varepsilon}^{T}(s)T_{1}\dot{\varepsilon}(s)dsd\lambda - e^{2k(t-d^{*})} \int_{t-d^{*}}^{t-d_{1}} \int_{\lambda}^{t} \dot{\varepsilon}^{T}(s)T_{2}\dot{\varepsilon}(s)dsd\lambda - e^{2k(t-d_{2})} \times \int_{t-d_{2}}^{t-d^{*}} \int_{\lambda}^{t} \dot{\varepsilon}^{T}(s)T_{3}\dot{\varepsilon}(s)dsd\lambda,$$
(17)

and  $\hat{U},\hat{V}$  and  $\hat{W}$  are positive diagonal matrices and from Assumption (A) and (B) we can get:

$$l_1 = \begin{bmatrix} \varepsilon(t) \\ \varphi(t) \end{bmatrix}^T \begin{bmatrix} -L_1 \hat{U} & L_2 \hat{U} \\ L_2 \hat{U} & -\hat{U} \end{bmatrix} \begin{bmatrix} \varepsilon(t) \\ \varphi(t) \end{bmatrix} \ge 0, \quad (18)$$

$$l_{2} = \begin{bmatrix} \varepsilon(t - \tau(t)) \\ \varphi(t - \tau(t)) \end{bmatrix}^{T} \begin{bmatrix} -L_{1}\hat{V} & L_{2}\hat{V} \\ L_{2}\hat{V} & -\hat{V} \end{bmatrix}$$

$$\begin{bmatrix} \varepsilon(t - \tau(t)) \\ \varphi(t - \tau(t)) \end{bmatrix} \ge 0,$$
(19)

$$l_{3} = \begin{bmatrix} \varepsilon(t) \\ \psi(t) \end{bmatrix}^{T} \begin{bmatrix} -L_{3}\hat{W} & L_{4}\hat{W} \\ L_{4}\hat{W} & -\hat{W} \end{bmatrix} \begin{bmatrix} \varepsilon(t) \\ \psi(t) \end{bmatrix} \ge 0, \quad (20)$$

From the (3), the following zero equalities with symmetric matrices P is considered.

$$2e^{2kt}\dot{\varepsilon}(t)p[-\dot{\varepsilon}(t) - A\varepsilon(t-\sigma) - KC\varepsilon(t) + B_1\varphi(t) + B_2\varphi(t-\tau(t)) + E\int_{t-r(t)}^t \varphi(s)ds - KD\psi(t)] = 0,$$
(21)

and P is the same with that in  $V_1$ , from Lemma 2, we have

$$-\sigma \int_{t-\sigma}^{t} \varepsilon^{T}(s)Q_{1}\varepsilon(s)ds \leq -\left[\int_{t-\sigma}^{t} \varepsilon(s)ds\right]^{T}Q_{1}\left[\int_{t-\sigma}^{t} \varepsilon(s)ds\right],$$
  

$$-r(t)\int_{t-r(t)}^{t} \varphi^{T}(s)dsQ_{2}\varphi(S)ds \leq -\left[\int_{t-r(t)}^{t} \varphi(s)ds\right]^{T}Q_{2}$$
  

$$\times \left[\int_{t-r(t)}^{t} \varphi(s)ds\right],$$
  

$$-\int_{t-d_{1}}^{t} \varepsilon^{T}(s)dsQ_{3}\varepsilon(s)ds \leq -\frac{1}{d_{1}}\left[\int_{t-d_{1}}^{t} \varepsilon(s)ds\right]^{T}Q_{3}$$
  

$$\times \left[\int_{t-d_{1}}^{t} \varepsilon(s)ds\right],$$
  

$$-\int_{t-d_{1}}^{t} \int_{\lambda}^{t} \dot{\varepsilon}^{T}(s)T_{1}\dot{\varepsilon}(s)dsd\lambda \leq -\frac{2}{d_{1}^{2}}\left[d_{1}\varepsilon(t) - \int_{t-d_{1}}^{t} \varepsilon(s)ds\right]^{T}$$
  

$$\times T_{1}\left[d_{1}\varepsilon(t) - \int_{t-d_{1}}^{t} \varepsilon(s)ds\right],$$
  
(22)

(1) When  $d_1 \leq \tau(t) \leq d^*$ ,

$$-\int_{t-d^*}^{t-d_1} \varepsilon^T(s) Q_4 \varepsilon(s) ds \leq -\frac{1}{d^* - d_1} [\int_{t-\tau(t)}^{t-d_1} \varepsilon(s) ds]^T$$

$$\times Q_4 [\int_{t-\tau(t)}^{t-d_1} \varepsilon(s) ds] - \frac{1}{d^* - d_1} [\int_{t-d^*}^{t-\tau(t)} \varepsilon(s) ds]^T Q_4$$

$$\times [\int_{t-d^*}^{t-\tau(t)} \varepsilon(s) ds],$$
(23)

$$-\int_{t-d_2}^{t-d^*} \varepsilon^T(s) Q_5 \varepsilon(s) ds \leq -\frac{1}{d_2 - d^*} [\int_{t-d_2}^{t-d^*} \varepsilon(s) ds]^T \times Q_5[\int_{t-d_2}^{t-d^*} \varepsilon(s) ds],$$
(24)

$$-\int_{t-d^*}^{t-d_1} \int_{\lambda}^{t} \dot{\varepsilon}^T(s) T_2 \dot{\varepsilon}(s) ds d\lambda \leq -\frac{2}{d^{*2} - d_1^2} [(d^* - d_1) \\ \times \varepsilon(t) - \int_{t-\tau(t)}^{t-d_1} \varepsilon(s) ds - \int_{t-d^*}^{t-\tau(t)} \varepsilon(s) ds]^T T_2 [(d^* - d_1)\varepsilon(t) \\ - \int_{t-\tau(t)}^{t-d_1} \varepsilon(s) ds - \int_{t-d^*}^{t-\tau(t)} \varepsilon(s) ds],$$

$$(25)$$

$$-\int_{t-d_{2}}^{t-d^{*}} \int_{\lambda}^{t} \dot{\varepsilon}^{T}(s) T_{3} \dot{\varepsilon}(s) ds d\lambda \leq -\frac{2}{d_{2}^{2}-d^{*2}} [(d_{2}-d^{*})\varepsilon(t) - \int_{t-d_{2}}^{t-d^{*}} \varepsilon(s) ds]^{T} T_{3} [(d_{2}-d^{*})\varepsilon(t) - \int_{t-d_{2}}^{t-d^{*}} \varepsilon(s) ds],$$
(26)

and for any scalar  $d_1 \leq \tau(t) \leq d^*$ , and any constant matrix  $Q_b \in \mathbb{R}^{n \times nn}$ ,  $Q_b = Q_b^T > 0$ , (b = 6, 7, 8), we can get the following inequalities from Lemma 3.

$$-\int_{t-d_{1}}^{t} \dot{\varepsilon}^{T}(s)Q_{6}\dot{\varepsilon}(s)ds \leq d_{1}\xi^{T}(t)UQ_{6}^{-1}U^{T}\xi(t) + 2\xi^{T}(t)U[\varepsilon(t) - \varepsilon(t - d_{1})], -\int_{t-d^{*}}^{t-\tau(t)} \dot{\varepsilon}^{T}(s)Q_{7}\dot{\varepsilon}(s)ds \leq (d^{*} - \tau(t))\xi^{T}(t)VQ_{7}^{-1}V^{T}\xi(t) + 2\xi^{T}(t)V[\varepsilon(t - \tau(t)) - \varepsilon(t - d^{*})], -\int_{t-\tau(t)}^{t-d_{1}} \dot{\varepsilon}^{T}(s)Q_{7}\dot{\varepsilon}(s)ds \leq (\tau(t) - d_{1})\xi^{T}(t)WQ_{7}^{-1}W^{T}\xi(t) + 2\xi^{T}(t)W[\varepsilon(t - d_{1}) - \varepsilon(t - \tau(t))], -\int_{t-d_{2}}^{t-d^{*}} \dot{\varepsilon}^{T}(s)Q_{8}\dot{\varepsilon}(s)ds \leq (d_{2} - d^{*})\xi^{T}(t)XQ_{8}^{-1}X^{T}\xi(t) + 2\xi^{T}(t)X[\varepsilon(t - d^{*}) - \varepsilon(t - d_{2})],$$
(27)

where  $\xi^T(t)$  will defined next and U, V, W, X are free-weighting matrices with appropriate dimensions.

$$\begin{split} \xi^{T}(t) = & [\varepsilon^{T}(t) \ \varepsilon^{T}(t-\sigma) \ \varepsilon^{T}(t-d_{1}) \ \varepsilon^{T}(t-d^{*}) \ \varepsilon^{T}(t-d_{2}) \\ \varepsilon^{T}(t-\tau(t)) \ \dot{\varepsilon}^{T}(t) \ \varphi^{T}(t) \ \varphi^{T}(t-\tau(t)) \ \psi^{T}(t) \\ & \int_{t-\sigma}^{t} \varepsilon^{T}(s) ds \ \int_{t-d_{1}}^{t} \varepsilon^{T}(s) ds \ \int_{t-r(t)}^{t} \varphi^{T}(s) ds \\ & \int_{t-\tau(t)}^{t-d_{1}} \varepsilon^{T}(s) ds \ \int_{t-d^{*}}^{t-\tau(t)} \varepsilon^{T}(s) ds \ \int_{t-d_{2}}^{t-d^{*}} \varepsilon^{T}(s) ds], \end{split}$$

By substituting (14)-(27) into (13) and use the relationship PK = G, we can obtain

$$\dot{V}(t) \le -e^{2kt}\xi^T(t)\Sigma_1\xi(t),$$
where  $\Sigma_1 = -\Xi_1 > 0$  with
$$(28)$$

$$\Xi_{1} = E + d_{1}e^{-2kd_{1}}UQ_{6}^{-1}U^{T} + (d^{*} - \tau(t))e^{-2kd^{*}}VQ_{7}^{-1}V^{T} + (\tau(t) - d_{1})e^{-2kd^{*}}WQ_{7}^{-1}W^{T} + (d_{2} - d^{*})e^{-2kd_{2}}XQ_{8}^{-1}X^{T}$$
(29)

According to (7) and (8), then one can obtain

$$E + d_{1}e^{-2kd_{1}}UQ_{6}^{-1}U^{T} + (d^{*} - d_{1})e^{-2kd^{*}}VQ_{7}^{-1}V^{T} + (d_{2} - d^{*})e^{-2kd_{2}}XQ_{8}^{-1}X^{T} < 0,$$

$$E + d_{1}e^{-2kd_{1}}UQ_{6}^{-1}U^{T} + (d^{*} - d_{1})e^{-2kd^{*}}WQ_{7}^{-1}W^{T} + (d_{2} - d^{*})e^{-2kd_{2}}XQ_{8}^{-1}X^{T} < 0,$$
(30)

then, according to the convex combination technique, we can obtain

$$\Xi_{1} = E + d_{1}e^{-2kd_{1}}UQ_{6}^{-1}U^{T} + (d^{*} - \tau(t))e^{-2kd^{*}}VQ_{7}^{-1}V^{T} + (\tau(t) - d_{1})e^{-2kd^{*}}WQ_{7}^{-1}V^{T} + (d_{2} - d^{*})e^{-2kd_{2}}XQ_{8}^{-1}V^{T} < 0,$$

$$< 0,$$

$$(31)$$

that is  $\dot{V}(t) \leq -e^{2kt}\xi^T(t)\Sigma_1\xi(t) < 0$ , (2) When  $d^* \leq \tau(t) \leq d_2$ , using Lemma 2, one get

$$-\int_{t-d^*}^{t-d_1} \varepsilon^T(s) Q_4 \varepsilon(s) ds \leq -\frac{1}{d^* - d_1} [\int_{t-d^*}^{t-d_1} \varepsilon(s) ds]^T Q_4$$
$$\times [\int_{t-d^*}^{t-d_1} \varepsilon(s) ds],$$
(32)

$$-\int_{t-d_2}^{t-d^*} \varepsilon^T(s) Q_5 \varepsilon(s) ds \leq -\frac{1}{d_2 - d^*} [\int_{t-\tau(t)}^{t-d^*} \varepsilon(s) ds]^T Q_5$$
$$\times \left[\int_{t-\tau(t)}^{t-d^*} \varepsilon(s) ds\right] - \frac{1}{d_2 - d^*} [\int_{t-d_2}^{t-\tau(t)} \varepsilon(s) ds]^T Q_5$$
$$\times \left[\int_{t-d_2}^{t-\tau(t)} \varepsilon(s) ds\right], \tag{33}$$

$$-\int_{t-d^{*}}^{t-d_{1}} \int_{\lambda}^{t} \dot{\varepsilon}^{T}(s) T_{2} \dot{\varepsilon}(s) ds d\lambda \leq -\frac{2}{d^{*2} - d_{1}^{2}} [(d^{*} - d_{1})\varepsilon(t) - \int_{t-d^{*}}^{t-d_{1}} \varepsilon(s) ds]^{T} T_{2} [(d^{*} - d_{1})\varepsilon(t) - \int_{t-d^{*}}^{t-d_{1}} \varepsilon(s) ds],$$
(34)

$$-\int_{t-d_{2}}^{t-d^{*}} \int_{\lambda}^{t} \dot{\varepsilon}^{T}(s) T_{3} \dot{\varepsilon}(s) ds d\lambda \leq -\frac{2}{d_{2}^{2}-d^{*2}} [(d_{2}-d^{*})\varepsilon(t) \\ -\int_{t-\tau(t)}^{t-d^{*}} \varepsilon(s) ds - \int_{t-d_{2}}^{t-\tau(t)} \varepsilon(s) ds]^{T} T_{3} [(d_{2}-d^{*})\varepsilon(t) \\ -\int_{t-\tau(t)}^{t-d^{*}} \varepsilon(s) ds - \int_{t-d_{2}}^{t-\tau(t)} \varepsilon(s) ds],$$

$$(35)$$

and for any scalar  $d^* \leq \tau(t) \leq d_2$ , and any constant matrix  $Q_b \in \mathbb{R}^{n \times nn}$ ,  $Q_b = Q_b^T > 0$ , (b = 6, 7, 8), we can get the following inequalities from Lemma 3.

$$-\int_{t-d_{1}}^{t} \dot{\varepsilon}^{T}(s)Q_{6}\dot{\varepsilon}(s)ds \leq d_{1}\eta^{T}(t)UQ_{6}^{-1}U^{T}\eta(t) +2\eta^{T}(t)U[\varepsilon(t)-\varepsilon(t-d_{1})], -\int_{t-d^{*}}^{t-d_{1}} \dot{\varepsilon}^{T}(s)Q_{7}\dot{\varepsilon}(s)ds \leq (d^{*}-d_{1})\eta^{T}(t)SQ_{7}^{-1}S^{T}\eta(t) +2\eta^{T}(t)S[\varepsilon(t-d_{1})-\varepsilon(t-d^{*})], -\int_{t-\tau(t)}^{t-d^{*}} \dot{\varepsilon}^{T}(s)Q_{8}\dot{\varepsilon}(s)ds \leq (\tau(t)-d^{*})\eta^{T}(t)YQ_{8}^{-1}Y^{T}\eta(t) +2\eta^{T}(t)Y[\varepsilon(t-d^{*})-\varepsilon(t-\tau(t))], -\int_{t-d_{2}}^{t-\tau(t)} \dot{\varepsilon}^{T}(s)Q_{8}\dot{\varepsilon}(s)ds \leq (d_{2}-\tau(t))\eta^{T}(t)ZQ_{8}^{-1}Z^{T}\eta(t) +2\eta^{T}(t)Z[\varepsilon(t-\tau(t))-\varepsilon(t-d_{2})],$$
(36)

where  $\eta^{T}(t)$  will defined next and U, S, Y, Z are free-

weighting matrices with appropriate dimensions.

$$\begin{split} \eta^{T}(t) = & [\varepsilon^{T}(t) \ \varepsilon^{T}(t-\sigma) \ \varepsilon^{T}(t-d_{1}) \ \varepsilon^{T}(t-d^{*}) \ \varepsilon^{T}(t-d_{2}) \\ & \varepsilon^{T}(t-\tau(t)) \ \dot{\varepsilon}^{T}(t) \ \varphi^{T}(t) \ \varphi^{T}(t-\tau(t)) \ \psi^{T}(t) \\ & \int_{t-\sigma}^{t} \varepsilon^{T}(s) ds \ \int_{t-d_{1}}^{t} \varepsilon^{T}(s) ds \ \int_{t-\tau(t)}^{t} \varphi^{T}(s) ds \\ & \int_{t-d^{*}}^{t-d_{1}} \varepsilon^{T}(s) ds \ \int_{t-\tau(t)}^{t-d^{*}} \varepsilon^{T}(s) ds \ \int_{t-d_{2}}^{t-\tau(t)} \varepsilon^{T}(s) ds], \end{split}$$

By substituting (14)-(22), (32)-(36) into (13) and use the relationship PK = G, we obtain

$$\dot{V}(t) \le -e^{2kt} \eta^T(t) \Sigma_2 \eta(t), \tag{37}$$

where 
$$\Sigma_2 = -\Xi_2 > 0$$
 with  
 $\Xi_2 = F + d_1 e^{-2kd_1} U Q_6^{-1} U^T + (d^* - d_1) e^{-2kd^*} S Q_7^{-1} S^T + (\tau(t) - d^*) e^{-2kd_2} Y Q_8^{-1} Y^T + (d_2 - \tau(t)) e^{-2kd_2} Z Q_8^{-1} Z^T,$ 
(38)

According to (9) and (10), then one can obtain

$$F + d_{1}e^{-2kd_{1}}UQ_{6}^{-1}U^{T} + (d^{*} - d_{1})e^{-2kd^{*}}SQ_{7}^{-1}S^{T} + (d_{2} - d^{*})e^{-2kd_{2}}YQ_{8}^{-1}Y^{T} < 0,$$

$$F + d_{1}e^{-2kd_{1}}UQ_{6}^{-1}U^{T} + (d^{*} - d_{1})e^{-2kd^{*}}SQ_{7}^{-1}S^{T} + (d_{2} - d^{*})e^{-2kd_{2}}ZQ_{8}^{-1}Z^{T} < 0,$$
(39)

then, according to the convex combination technique, we can obtain

$$\Xi_{2} = F + d_{1}e^{-2kd_{1}}UQ_{6}^{-1}U^{T} + (d^{*} - d_{1})e^{-2kd^{*}}SQ_{7}^{-1}S^{T} + (\tau(t) - d^{*})e^{-2kd_{2}}YQ_{8}^{-1}Y^{T} + (d_{2} - \tau(t))e^{-2kd_{2}} ZQ_{8}^{-1}Z^{T} < 0,$$
(40)

that is  $\dot{V}(t) \leq -e^{2kt}\eta^T(t)\Sigma_2\eta(t) < 0$ ,

Therefore, if (7)-(10) are satisfied, then (3) or (4) is guaranteed to be globally exponentially stable for  $d(t) \in [d_1, d_2]$ .

On the other hand, it is not difficult to obtain the following inequalities:

$$V_{1}(0) \leq \lambda_{\max}(P) \|\varepsilon(0) - A \int_{-\sigma}^{0} \varepsilon(s) ds\|^{2} \leq \lambda_{\max}(P)$$

$$\times (\|\Phi(0)\| - \|A\| \int_{-\sigma}^{0} \|\varepsilon(s)\| ds)^{2} \leq \lambda_{\max}(P) \|\Phi(0)\|^{2}$$

$$+ \|A\|^{2} \int_{-\sigma}^{0} \|\varepsilon(s)\|^{2} ds \leq \lambda_{\max}(P) (1 + \sigma \|A\|^{2})$$

$$\times \sup_{-\tau \leq s \leq 0} \|\Phi(s)\|^{2},$$
(41)

$$V_{2}(0) \leq (d_{2}\lambda_{\max}(R_{1}) + d_{1}\lambda_{\max}(R_{2}) + d_{2}\lambda_{\max}(R_{3}) + d^{*}\lambda_{\max}(R_{4} + d_{2}\gamma_{1}\lambda_{\max}(R_{5}) + \sigma\lambda_{\max}(R_{6})) \times \sup_{-\tau \leq s \leq 0} \|\Phi(s)\|^{2},$$
(42)

Open Science Index, Mathematical and Computational Sciences Vol:8, No:5, 2014 publications.waset.org/9999220.pdf

$$V_{3}(0) \leq \sigma \lambda_{\max}(Q_{1}) \int_{-\sigma}^{0} \int_{\theta}^{0} e^{T}(s)\varepsilon(s)dsd\theta + \bar{r}\lambda_{\max}(Q_{2})$$

$$\times \int_{-\bar{r}}^{0} \int_{\theta}^{0} \varphi^{T}(s)\varphi(s)dsd\theta + \lambda_{\max}(Q_{3}) \int_{-d_{1}}^{0} \int_{\theta}^{0} \varepsilon^{T}(s)\varepsilon(s)$$

$$\times dsd\theta + \lambda_{\max}(Q_{4}) \int_{-d^{*}}^{-d_{1}} \int_{\theta}^{0} \varepsilon^{T}(s)\varepsilon(s)dsd\theta + \lambda_{\max}(Q_{5})$$

$$\times \int_{-d_{2}}^{-d^{*}} \int_{\theta}^{0} \varepsilon^{T}(s)\varepsilon(s)dsd\theta + \lambda_{\max}(Q_{6}) \int_{-d_{1}}^{0} \int_{\theta}^{0} \dot{\varepsilon}^{T}(s)\dot{\varepsilon}(s)$$

$$\times dsd\theta + \lambda_{\max}(Q_{7}) \int_{-d^{*}}^{-d_{1}} \int_{\theta}^{0} \dot{\varepsilon}^{T}(s)\dot{\varepsilon}(s)dsd\theta + \lambda_{\max}$$

$$\times (Q_{8}) \int_{-d_{2}}^{-d^{*}} \int_{\theta}^{0} \dot{\varepsilon}^{T}(s)\dot{\varepsilon}(s)dsd\theta,$$
(43)

$$\begin{aligned} \dot{\varepsilon}^{T}(s)\dot{\varepsilon}(s) &\leq 6[\lambda_{\max}(A^{T}A) + \lambda_{\max}(C^{T}K^{T}KC) \\ &+ \gamma_{1}^{2}\lambda_{\max}(B_{1}^{T}B_{1}) + \gamma_{1}^{2}\lambda_{\max}(B_{2}^{T}B_{2}) + \bar{r}\gamma_{1}^{2}\lambda_{\max}(\tilde{E}^{T}\tilde{E}) \\ &+ \gamma_{2}^{2}\lambda_{\max}(D^{T}K^{T}KD)] \sup_{-\tau \leq s \leq 0} \|\Phi(s)\|^{2}, \end{aligned}$$

$$(44)$$

where  

$$\gamma_{1} = \max_{1 \leq i \leq n} \{ |\phi_{i}^{-}|, |\phi_{i}^{+}| \}, \gamma_{2} = \max_{1 \leq j \leq m} \{ |\omega_{j}^{-}|, |\omega_{j}^{+}| \}.$$

$$\bar{r}\lambda_{\max}(Q_{2}) \int_{-\bar{r}}^{0} \int_{\theta}^{0} \varphi^{T}(s)\varphi(s)dsd\theta \leq \frac{\bar{r}^{3}\gamma_{1}^{2}}{2}\lambda_{\max}(Q_{2})$$

$$\times \sup_{-\tau \leq s \leq 0} \|\Phi(s)\|^{2},$$
(45)

$$V_{4}(0) \leq [d_{1}^{3}\lambda_{\max}(T_{1}) + (d^{*3} - d_{1}^{3})\lambda_{\max}(T_{2}) + (d_{2}^{3} - d^{*3}) \\ \times \lambda_{\max}(T_{3})]\lambda_{\max}(A^{T}A) + \lambda_{\max}(C^{T}K^{T}KC) + \gamma_{1}^{2} \\ \times \lambda_{\max}(B_{1}^{T}B_{1}) + \gamma_{1}^{2}\lambda_{\max}(B_{2}^{T}B_{2}) + \bar{r}\gamma_{1}^{2}\lambda_{\max}(\tilde{E}^{T}\tilde{E}) + \gamma_{2}^{2} \\ \times \lambda_{\max}(D^{T}K^{T}KD)] \sup_{-\tau \leq s \leq 0} \|\Phi(s)\|^{2},$$
(46)

$$\begin{split} &\alpha = [\lambda_{\max}(P)(1+\sigma \|A\|^2) + d_2\lambda_{\max}(R_1) + d_1\lambda_{\max}(R_2) \\ &+ d_2\lambda_{\max}(R_3) + d^*\lambda_{\max}(R_4 + d_2\gamma_1\lambda_{\max}(R_5) \\ &+ \sigma\lambda_{\max}(R_6) + \frac{\sigma^3}{6}\lambda_{\max}(Q_1) + \frac{\bar{r}^3}{6}\gamma_1^2\lambda_{\max}(Q_2) \\ &+ \frac{d_1^3}{6}\lambda_{\max}(Q_3) + \frac{d^{*2} - d_1^2}{6}\lambda_{\max}(Q_4) + \frac{d_2^2 - d^{*2}}{6} \\ &\times \lambda_{\max}(Q_5)] + [3d_1^2\lambda_{\max}(Q_6) + 3(d^{*2} - d_1^2)\lambda_{\max}(Q_7) \\ &+ 3(d_2^2 - d_1^2)\lambda_{\max}(Q_8) + d_1^3\lambda_{\max}(T_1) \\ &+ (d^{*3} - d_1^3)\lambda_{\max}(T_2) + (d_2^3 - d^{**})\lambda_{\max}(T_3)] \\ &\times [\lambda_{\max}(A^T A) + \lambda_{\max}(C^T K^T K C) + \gamma_1^2\lambda_{\max}(B_1^T B_1) \\ &+ \gamma_1^2\lambda_{\max}(B_2^T B_2) + \bar{r}^2\gamma_1^2\lambda_{\max}(\tilde{E}^T \tilde{E}) \\ &+ \gamma_2^2\gamma_1^2\lambda_{\max}(D^T K^T K D)], \end{split}$$

Then we can get:

$$V(0) \le \alpha \sup_{-\tau \le s \le 0} \|\Phi(t)\|^2 < \infty,$$
(47)

Considering  $V_1(t)$ , one can easily obtain that

$$\|\varepsilon(t) - A \int_{t-\sigma}^{t} \varepsilon(s) ds\|^{2} \leq \frac{1}{e^{2kt} \lambda_{\min}(P)} [\varepsilon(t) - A \qquad (48)$$

$$\times \int_{t-\sigma}^{t} \varepsilon(s) ds]^{T} P[\varepsilon(t) - A \int_{t-\sigma}^{t} \varepsilon(s) ds] \leq \frac{V(t)}{e^{2kt} \lambda_{\min}(P)}$$

$$\leq \frac{V(0)}{e^{2kt} \lambda_{\min}(P)} ,$$

Which implies that

$$\|\varepsilon(t)\| \le \|A \int_{t-\sigma}^{t} \varepsilon(s) ds\| + \sqrt{\frac{V(0)}{e^{2kt} \lambda_{\min}(P)}}$$

$$\le \|A\| \int_{t-\sigma}^{t} \|\varepsilon(s)\| ds + \sqrt{\frac{V(0)}{e^{2kt} \lambda_{\min}(P)}} ,$$
(49)

Where  $||A|| = \sqrt{\sum_{i=1}^{n} \sum_{j=1}^{n} a_{ij}^2}$ , And by the well-known Gronwall inequality which can be found in [35], it yields

$$\|\varepsilon(t)\| \leq \sqrt{\frac{V(0)}{e^{2kt}\lambda_{\min}(P)}} e^{\|A\|\sigma} \leq \sqrt{\frac{\alpha}{\lambda_{\min}(P)}} e^{\|A\|\sigma}$$

$$\times \sup_{-\tau \leq s \leq 0} \|\Phi(s)\| e^{-kt},$$
(50)

Then from the Definition 1, the system (3) or (4) is exponentially stable with convergence rate k, and the proof is completed.

In particular, the model (3) becomes the well-known case when  $\sigma = 0$  and the system has been directly or indirectly investigated by a lot of authors, see [26-29].

When there is no time delay in the leakage term in errorstate system (3) or (4), that is  $\sigma = 0$ , we get:

$$\dot{\varepsilon}(t) = -(A + KC)\varepsilon(t) + B_1\varphi(t) + B_2\varphi(t - \tau(t)) + \tilde{E} \int_{t-r(t)}^t \varphi(s)ds - KD\psi(t),$$
(51)

where  $\tau(t)$  and r(t) are the discrete time-varying delays and the distributed time-varying delays satisfy the following inequality:

$$0 < d_1 \le \tau(t) \le d_2, \quad 0 < r(t) \le \bar{r}, \quad \dot{\tau}(t) \le \mu < \infty,$$

 $d_1, d_2, \bar{r}$  and  $\mu$  are constants. for system (51), we can obtain the following result.

**Corollary 1** For the given scalars  $d_1, d_2, \bar{r}$  and  $\mu < \infty$ , the equilibrium point of the error-state system (51) is globally exponentially stable with the rate index k, if there exist  $P > 0, R_l > 0, (l = 1, 2, \cdots, 5), Q_m > 0,$  $(m = 2, 3, \cdots, 8), T_n > 0, (n = 1, 2, 3),$  any matrices  $G, U_k, V_k, W_k, X_k, Y_k, Z_k, S_k (k = 1, 2)$ , and the diagonal matrices  $\hat{U} > 0$ ,  $\hat{V} > 0$ ,  $\hat{W} > 0$  such that the following LMIs hold.

$$H_{14\times14} + d_1 e^{-2kd_1} U Q_6^{-1} U^T + (d^* - d_1) e^{-2kd^*} V \times Q_7^{-1} V^T + (d_2 - d^*) e^{-2kd_2} X Q_8^{-1} X^T < 0,$$
(52)

$$H_{14\times14} + d_1 e^{-2kd_1} U Q_6^{-1} U^T + (d^* - d_1) e^{-2kd^*} W \times Q_7^{-1} W^T + (d_2 - d^*) e^{-2kd_2} X Q_8^{-1} X^T < 0,$$
(53)

$$I_{14\times 14} + d_1 e^{-2kd_1} U Q_6^{-1} U^T + (d^* - d_1) e^{-2kd^*} S \times Q_7^{-1} S^T + (d_2 - d^*) e^{-2kd_2} Y Q_8^{-1} Y^T < 0,$$
(54)

$$\begin{split} H_{1,1} &= 2kP - PA - A^TP - GC - C^TG^T + R_1 + R_2 \\ &+ R_3 + R_4 + d_1Q_3 + (d^* - d_1)Q_4 + (d_2 - d^*)Q_5 \\ &- 2e^{-2kd_1}T_1 - 2\frac{d^* - d_1}{d^* + d_1}e^{-2kd^*}T_2 - L_1\hat{U} - L_3\hat{W} \\ &+ e^{-2kd_1}U_1 + e^{-2kd_1}U_1^T - 2\frac{d_2 - d^*}{d_2 + d^*}e^{-2kd_2}T_3 \\ H_{1,2} &= e^{-2kd_1}(-U_1 + U_2^T), \quad H_{1,6} = -C^TG^T, \\ H_{1,7} &= PB_1 + L_2\hat{U}, \quad H_{1,8} = PB_2 \\ H_{1,9} &= -GD + L_4\hat{W}, \quad H_{1,10} = \frac{2}{d_1}e^{-2kd^*}T_2, \\ H_{1,11} &= P\tilde{E}, \quad H_{1,12} = \frac{2}{d^* + d_1}e^{-2kd^*}T_2, \\ H_{1,13} &= \frac{2}{d^* + d_1}e^{-2kd^*}T_2, \quad H_{1,14} = \frac{2}{d_2 + d^*}e^{-2kd_2}T_3, \\ H_{2,2} &= e^{-2kd_1}(U_2^T + U_2) - e^{-2kd_1}R_2 + e^{-2kd^*}(W_1 + W_1^T), \\ H_{2,5} &= e^{-2kd^*}(-W_1 + W_2^T) \\ H_{3,3} &= -e^{-2kd^*}R_4 + e^{-2kd^*}(-V_1 - V_1)^T + e^{-2kd_2} \\ \times (X_1 + X_1^T), \\ H_{3,4} &= -e^{-2kd_2}(-X_1 + X_2^T), \quad H_{3,5} &= -e^{-2kd^*}(V_1 - V_2^T), \\ H_{4,4} &= -e^{-2kd_2}R_3 + e^{-2kd_2}(-X_2 - X_2^T), \\ H_{5,5} &= -L_1\hat{V} - (1 - \mu)e^{-2kd^*}R_1 + e^{-2kd^*}(V_2 + V_2^T) \\ + e^{-2kd^*}(-W_2 - w_2^T), \\ H_{5,8} &= L_2\hat{V}, \\ H_{6,6} &= -2P + d_1Q_6 + \frac{d_1^2}{2}T_1 + \frac{d^{*2} - d_1^2}{2}T_2 + \frac{d_2^2 - d^{*2}}{2}T_3 \\ + (d^* - d_1)Q_7 + (d_2 - d^*)Q_8, \\ H_{6,7} &= PB_1, \quad H_{6,8} &= PB_2, \quad H_{6,9} &= -GD, \quad H_{6,11} &= P\tilde{E}, \\ H_{7,7} &= R_5 + \bar{r}^2Q_2 - \hat{U}, \quad H_{8,8} &= -(1 - \mu)e^{-2kd^*}R_5 - \hat{V}, \\ H_{9,9} &= -\hat{W}, \quad E_{10,11} &= D^TG^TA, \\ H_{10,10} &= -\frac{1}{d_1}e^{-2kd_1}Q_3 - \frac{2}{d_1^2}e^{-2kd_1}T_1, \\ H_{11,11} &= -e^{-2k\bar{r}}Q_2, \\ \end{array}$$

$$\begin{split} H_{12,12} &= -\frac{1}{d^* - d_1} e^{-2kd^*} Q_4 - \frac{2}{d^{*2} - d_1^2} e^{-2kd^*} T_2, \\ H_{12,13} &= -\frac{2}{d^{*2} - d_1^2} e^{-2kd^*} T_2, \\ H_{13,13} &= -\frac{1}{d^* - d_1} e^{-2kd^*} Q_4 - \frac{2}{d^{*2} - d_1^2} e^{-2kd^*} T_2, \\ H_{14,14} &= -\frac{1}{d_2 - d^*} e^{-2kd_2} Q_5 - \frac{2}{d_2^2 - d^{*2}} e^{-2kd_2} T_3 \\ I_{1,13} &= \frac{2}{d_2 + d^*} e^{-2kd_2} T_3 \\ I_{2,2} &= e^{-2kd_1} R_2 + e^{-2kd_1} (-U_2 - U_2^T) + e^{-2kd^*} (S_1 + S_1^T), \\ I_{3,4} &= e^{-2kd^*} (-S_1 + S_2^T), \quad I_{3,6} = 0, \\ I_{3,3} &= e^{-2kd^*} R_4 + e^{-2kd^*} (-S_2 - S_2^T) + e^{-2kd_2} (Y_1 + Y_1^T), \\ I_{4,5} &= 0, \quad I_{4,6} &= e^{-2kd_2} (Y_1 + Y_2^T), \\ I_{4,4} &= e^{-2kd_2} (-Z_2 - Z_2^T) - e^{-2kd_2} R_3, \\ I_{5,6} &= e^{-2kd_2} (Z_1 - Z_2^T), \\ I_{5,5} &= -(1 - \mu)e^{-2kd_2} R_1 + e^{-2kd_2} (-Y_2 - Y_2^T) \\ &+ e^{-2kd_2} (Z_2 + Z_2^T), \quad I_{8,8} &= -(1 - \mu)e^{-2kd_2} R_5 + \hat{V}, \\ I_{13,13} &= -\frac{1}{d_2 - d^*} e^{-2kd_2} Q_5 - \frac{2}{d_2^2 - d^{*2}} e^{-2kd_2} T_3, \\ I_{14,14} &= -\frac{1}{d_2 - d^*} e^{-2kd_2} Q_5 - \frac{2}{d_2^2 - d^{*2}} e^{-2kd_2} T_3, \\ \end{split}$$

the other entries of H is 0 and the other entries of I is the same as H, and  $d^* \in (d_1, d_2), d^* = \lambda d_1 + (1 - \lambda)d_2, \lambda \in (0, 1)$ , The gain matrix of state estimator is given by

$$K = P^{-1}G, (56)$$

*Proof:* Consider a novel augmented of Lyapunov-Krasovskii functional for the system (51) as follows:

$$V(t) = V_1(t) + V_2(t) + V_3(t) + V_4(t),$$
(57)

where

$$V_1(t) = e^{2kt} \varepsilon(t)^T P \varepsilon(t)$$

$$V_{2}(t) = \int_{t-\tau(t)}^{t} e^{2ks} \varepsilon^{T}(s) R_{1}\varepsilon(s) ds$$
  
+ 
$$\int_{t-d_{1}}^{t} e^{2ks} \varepsilon^{T}(s) R_{2}\varepsilon(s) ds$$
  
+ 
$$\int_{t-d_{2}}^{t} e^{2ks} \varepsilon^{T}(s) R_{3}\varepsilon(s) ds$$
  
+ 
$$\int_{t-d^{*}}^{t} e^{2ks} \varepsilon^{T}(s) R_{4}\varepsilon(s) ds$$
  
+ 
$$\int_{t-\tau(t)}^{t} e^{2ks} \varphi^{T}(s) R_{5}\varphi(s) ds$$

$$\begin{aligned} V_{3}(t) = \bar{r} \int_{-\bar{r}}^{0} \int_{t+\theta}^{t} e^{2ks} \varphi^{T}(s) Q_{2}\varphi(s) ds d\theta \\ + \int_{-d_{1}}^{0} \int_{t+\theta}^{t} e^{2ks} \varepsilon^{T}(s) Q_{3}\varepsilon(s) ds d\theta \\ + \int_{-d_{1}}^{-d_{1}} \int_{t+\theta}^{t} e^{2ks} \varepsilon^{T}(s) Q_{4}\varepsilon(s) ds d\theta \\ + \int_{-d_{2}}^{-d^{*}} \int_{t+\theta}^{t} e^{2ks} \varepsilon^{T}(s) Q_{5}\varepsilon(s) ds d\theta \\ + \int_{-d_{1}}^{0} \int_{t+\theta}^{t} e^{2ks} \dot{\varepsilon}^{T}(s) Q_{6}\dot{\varepsilon}(s) ds d\theta \\ + \int_{-d_{*}}^{-d_{1}} \int_{t+\theta}^{t} e^{2ks} \dot{\varepsilon}^{T}(s) Q_{7}\dot{\varepsilon}(s) ds d\theta \\ + \int_{-d_{2}}^{-d^{*}} \int_{t+\theta}^{t} e^{2ks} \dot{\varepsilon}^{T}(s) Q_{8}\dot{\varepsilon}(s) ds d\theta \\ + \int_{-d_{2}}^{-d^{*}} \int_{t+\theta}^{t} e^{2ks} \dot{\varepsilon}^{T}(s) Q_{8}\dot{\varepsilon}(s) ds d\theta \\ \end{aligned}$$

$$Y_{4}(t) = \int_{t-d_{1}} \int_{\theta} \int_{\lambda} e^{2ks} \dot{\varepsilon}^{T}(s) T_{1} \dot{\varepsilon}(s) ds d\lambda d\theta + \int_{t-d^{*}}^{t-d_{1}} \int_{\theta}^{t} \int_{\lambda}^{t} e^{2ks} \dot{\varepsilon}^{T}(s) T_{2} \dot{\varepsilon}(s) ds d\lambda d\theta + \int_{t-d_{2}}^{t-d^{*}} \int_{\theta}^{t} \int_{\lambda}^{t} e^{2ks} \dot{\varepsilon}^{T}(s) T_{3} \dot{\varepsilon}(s) ds d\lambda d\theta,$$

According to the similar procedure discussed in Theorem 1, we obtain

(1) When  $d_1 \leq \tau(t) \leq d^*$ ,  $\dot{V}(t) \leq e^{2kt}\xi^T [H + d_1 e^{-2kd_1} U Q_6^{-1} U^T + (d^* - \tau(t)) e^{-2kd^*} \times V Q_7^{-1} V^T + (\tau(t) - d_1) e^{-2kd^*} W Q_7^{-1} V^T + (d_2 - d^*) \times e^{-2kd_2} X Q_8^{-1} V^T ](t) \xi(t) < 0,$ (58)

where

$$\begin{split} \bar{\xi}^T(t) = & [\varepsilon^T(t) \quad \varepsilon^T(t-d_1) \quad \varepsilon^T(t-d^*) \quad \varepsilon^T(t-d_2) \\ & \varepsilon^T(t-\tau(t)) \quad \dot{\varepsilon}^T(t) \quad \varphi^T(t) \quad \varphi^T(t-\tau(t)) \quad \psi^T(t) \\ & \int_{t-d_1}^t \varepsilon^T(s) ds \quad \int_{t-r(t)}^t \varepsilon^T(s) ds \quad \int_{t-\tau(t)}^{t-d_1} \varepsilon^T(s) ds \\ & \int_{t-d^*}^{t-\tau(t)} \varepsilon^T(s) ds \quad \int_{t-d_2}^{t-d^*} \varepsilon^T(s) ds], \end{split}$$

(2) When  $d^* \leq \tau(t) \leq d_2$ ,

$$\dot{V}(t) \leq e^{2kt} \xi^{T} [I + d_{1}e^{-2kd_{1}}UQ_{6}^{-1}U^{T} + (d^{*} - \tau(t))e^{-2kd^{*}} \\ \times VQ_{7}^{-1}V^{T} + (\tau(t) - d_{1})e^{-2kd^{*}}WQ_{7}^{-1}W^{T} + (d_{2} - d^{*}) \\ \times e^{-2kd_{2}}XQ_{8}^{-1}X^{T}](t)\xi(t) < 0,$$
(59)

where

$$\begin{split} \bar{\eta}^{T}(t) = & [\varepsilon^{T}(t) \quad \varepsilon^{T}(t-d_{1}) \quad \varepsilon^{T}(t-d^{*}) \quad \varepsilon^{T}(t-d_{2}) \\ & \varepsilon^{T}(t-\tau(t)) \quad \dot{\varepsilon}^{T}(t) \quad \varphi^{T}(t) \quad \varphi^{T}(t-\tau(t)) \quad \psi^{T}(t) \\ & \int_{t-d_{1}}^{t} \varepsilon^{T}(s) ds \quad \int_{t-r(t)}^{t} \varphi^{T}(s) ds \quad \int_{t-d^{*}}^{t-d_{1}} \varepsilon^{T}(s) ds \\ & \int_{t-\tau(t)}^{t-d^{*}} \varepsilon^{T}(s) ds \quad \int_{t-d_{2}}^{t-\tau(t)} \varepsilon^{T}(s) ds], \end{split}$$

From the (58) and (59), by using the convex combination technique and Schur complement, the (60) are equivalent to (52)-(54). This completes the proof.

**Remark 1** It is noted that [25] discussed the error-state system (3) and (4) is globally asymptotically stable and it did not use the delay departing technique, in this paper, Theorem 1 proposes an improved exponential stability condition for neural networks with mixed time-delays. we divided  $[d_1, d_2]$  into  $[d_1, d^*]$  and  $[d^*, d_2]$ , which  $d^*$  satisfy linear combination, Each segments has a different Lyapunov matrix, which can obtain less conservative results. and the constructed Lyapunov functional V(t) is much more general and desirable than that in [25].

**Remark 2** Although the system (51) has been studied in [27]-[28], the results in [27] and [28] can not tackle the estimation problems when the derivative of the time-varying is not less than one, and they did not have the leakage delay. **Remark 3** The author of [34] investigated the system with distributed delay, the system in this paper also has leakage delay  $\sigma$ , so [34] is a special situation of this paper's system when  $d_1 = 0$  and  $\sigma = 0$ . that is to say this paper discuss the discrete with certain bounds.

## IV. NUMERICAL EXAMPLES

In this section, three examples with be given to illustrate the usefulness of obtained results.

**Example 1** Consider the error-state system (3) and (4) with the following parameters

$$\begin{split} A &= \begin{bmatrix} 2 & 0 & 0 \\ 0 & 3 & 0 \\ 0 & 0 & 2 \end{bmatrix}, B_1 = \begin{bmatrix} 0.2 & -0.2 & 0.4 \\ -0.4 & 2 & 0.2 \\ 0.2 & 0.4 & -0.4 \end{bmatrix}, \\ B_2 &= \begin{bmatrix} 0.2 & 0.2 & 0.2 \\ 0.2 & 0.2 & 0.2 \\ 0.2 & 0.2 & 0.2 \end{bmatrix}, \tilde{E} = \begin{bmatrix} 0.2 & 0.1 & 0.1 \\ 0.1 & 0.2 & 0.1 \\ 0.1 & 0.1 & 0.2 \end{bmatrix}, \\ C &= \begin{bmatrix} 1 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & 1 \end{bmatrix}, D = \begin{bmatrix} 1 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & 1 \end{bmatrix}, \\ J &= \begin{bmatrix} 2sint + 0.03t^2 \\ 3cost - 0.03t^2 \\ 2cost - 0.03t^2 \end{bmatrix}, \end{split}$$

Where  $L_1 = diag\{0, 0, 0\}, L_3 = diag\{0, 0, 0\}, L_2 = L_4 = diag\{-0.25, -0.25, 0.25\}$ . If that  $\tau(t) = 3sin^2t + 0.01$ ,  $r(t) = cos^2t, \sigma = 0$ , we can easily get  $d_1 = 0.01, d_2 = 3.01$ ,  $\mu = 3$  and r = 1. when  $k = 0.01, \lambda = 0.5$ , by Corollary 1 and the LMI toolbox in solving (51), we have the estimator gain matrix P and G as follows:

	0.0416	0.0257	0.0048	]
P =	0.0257	0.0455	-0.0015	,
	0.0048	-0.0015	0.0198	
	0.0007	0.0007	0.0000 ]	
G =	0.0014	0.0002	0.0000	,
	[-0.0002]	0.0000	0.0000	

870



Fig. 1. Error trajectories of the state estimation in case of  $\sigma = 0.01$ .

Thus, the estimator gain matrix K as follows

$$K = P^{-1}G = \begin{bmatrix} -0.0006 & 0.0239 & 0.0000\\ 0.0302 & -0.0084 & 0.0000\\ -0.0069 & -0.0070 & 0.0000 \end{bmatrix},$$

It is easy to known that  $\tau(t)$  is a time-varying one and  $\mu = 3 \ge 1.5 \ge 1$ , [30,32,33] fail to tackle the state estimation problem, though [34] succuss to tackle the state estimation problem when  $\mu \ge 1$ , the variation range of  $\tau(t)$  we get is bigger than it. when  $\mu = 3$  we known it satisfied the corollary 1 and when  $k \le 0.4711$  and  $\lambda = 0.5$  we can always obtain a K. If that  $\tau(t) = 0.9sint + 1$ , we can easily get  $d_1 = 0.1$ ,  $d_2 = 1.9$ ,  $\mu = 0.9$ , if  $\bar{r} = 1$ ,  $\sigma = 0.01$ , k = 0.01,  $\lambda = 0.5$ , by using the Theorem 1, we can get the corresponding gain matrix as follows.

$$K = P^{-1}G = \begin{bmatrix} 0.0034 & 0.0456 & 0\\ 0.0470 & -0.0189 & 0\\ -0.0188 & -0.0087 & 0 \end{bmatrix},$$

It can be seen that the dynamical behavior of (3) or (4) id global exponential stable when  $\sigma = 0.01, k = 0.01$ , the trajectories of the error system (3) or (4) converge to zero as shown in Fig 1.

**Example 2** Consider the error-state system (3) and (4) with the following parameters

TABLE I Allowable Upper Bound of  $d_2$  with Various  $d_1$  And  $\sigma$ 

$d_1$	0.01	0.02	0.05	0.1
$\sigma = 0$	9.4212	8.8106	6.7741	2.8619
$\sigma = 0.01$	9.4205	8.8106	6.7678	2.8618
$\sigma = 0.1$	9.4023	8.7569	6.5624	2.3646
$\sigma = 1$	8.9460	7.7203	3.5692	infeasible

TABLE II Allowable Upper Bound of k with Various  $\sigma$  and  $d_2$ 

σ	0	0.1	0.2	0.5	1
$d_2 = 1.5$	0.6738	0.6707	0.6634	0.6344	0.5669
$d_2 = 3$	0.4722	0.4693	0.4643	0.4441	0.4008

$$A = \begin{bmatrix} 2 & 0 & 0 \\ 0 & 3 & 0 \\ 0 & 0 & 2 \end{bmatrix}, B_1 = \begin{bmatrix} 0.2 & -0.2 & 0.4 \\ -0.4 & 2 & 0.2 \\ 0.2 & 0.4 & -0.4 \end{bmatrix},$$
$$B_2 = \begin{bmatrix} 0.2 & 0.2 & 0.2 \\ 0.2 & 0.2 & 0.2 \\ 0.2 & 0.2 & 0.2 \end{bmatrix}, \tilde{E} = \begin{bmatrix} 0.2 & 0.1 & 0.1 \\ 0.1 & 0.2 & 0.1 \\ 0.1 & 0.1 & 0.2 \end{bmatrix},$$
$$C = D = \begin{bmatrix} 1 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & 1 \end{bmatrix}, L_1 = L_3 = \begin{bmatrix} 0 & 0 & 0 \\ 0 & 0 & 0 \\ 0 & 0 & 0 \end{bmatrix},$$
$$L_2 = L_4 = \begin{bmatrix} -0.25 & 0 & 0 \\ 0 & -0.25 & 0 \\ 0 & 0 & -0.25 \end{bmatrix},$$

If  $\mu = 3, r = 1, \lambda = 0.5, k = 0.01$ . by Theorem 1 and the LMI toolbox in solving (3) or (4), we have estimated the allowable upper bound of  $d_2$  when  $d_1$  and  $\sigma$  are varied in Table I.

**Example 3** Consider the error-state system (3) and (4) with the following parameters

$$\begin{split} A &= \begin{bmatrix} 2 & 0 & 0 \\ 0 & 3 & 0 \\ 0 & 0 & 2 \end{bmatrix}, B_1 = \begin{bmatrix} 0.2 & -0.2 & 0.4 \\ -0.4 & 2 & 0.2 \\ 0.2 & 0.4 & -0.4 \end{bmatrix}, \\ B_2 &= \begin{bmatrix} 0.2 & 0.2 & 0.2 \\ 0.2 & 0.2 & 0.2 \\ 0.2 & 0.2 & 0.2 \end{bmatrix}, \tilde{E} = \begin{bmatrix} 0.2 & 0.1 & 0.1 \\ 0.1 & 0.2 & 0.1 \\ 0.1 & 0.1 & 0.2 \end{bmatrix}, \\ C &= \begin{bmatrix} 1 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & 1 \end{bmatrix}, D = \begin{bmatrix} 1 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & 1 \end{bmatrix}, \end{split}$$

If giving the parameters as  $L_1 = L_3 = diag\{0, 0, 0\}, L_2 = L_4 = diag\{-0.25, -0.25, 0.25\}, d_1 = 0.01, \mu = 1.5, \lambda = 0.5$ and r = 1. by Theorem 1 and the LMIs toolbox in solving (3) or (4), we tackle the state estimation problem when  $\sigma$  and  $d_2$  are varying, and obtain the allowable upper bound of k in Table II.

#### V. CONCLUSIONS

In this paper, the state estimation problem for neural networks with mixed time-varying delays has been studied, through the LMI approach and delay departing measurements, an exponential state estimator is designed to estimate the neuron state and verify the dynamics of the estimation error is globally exponentially stable, and by dividing the discrete delay interval into multiple segments, the upper bounds of some variables are obtained. Finally, numerical examples have been given to illustrate the effectiveness of the proposed methods.

#### REFERENCES

- Y. Liu, Z. Wang, X. Liu, "Global exponential stsbility of generalized recurrent neural networks with discrete and distributed delays," Neural Networks 19(2006)667-675.
- [2] Y. Wang , Z. Wang , J. Liang ,"On robust stability of stochastic genetic regulatory networks with time-delays : a delay fractioning papproach," IEEE Trans.Syst.Man Cybern.PartB 40(2010)729-740.
- [3] X.Liu, "Delay-dependent  $H \propto$  control for uncertain fuzzy systems with time-varying delays," Nonlinear Analysis: Theory, Methods Applications 68(2008)1352-1361.
- [4] S. Y. Xu, Janmes Lam, "A new LMI condition for delay-dependent asymptotic stability of delayed Hopfield neural networks," IEEE Trans Circuits Syst.53(2006)230-235.
- [5] Y.He,M.Wu, "An improved global asymptotic stability criterion for delayed cellular neural networks," IEEE Trans, Neural Networks 17(2006)250-253.
- [6] X.Y.Lou, B.T.Cui, "On the global robust asymptotic stability of BAM neural networks with time-varying delays," Neurocomputing 70(2006)273-279.
- [7] W.H.Chen, X.M.Lu, "Delay-dependent exponential stability of neural networks with variable delay" :An LMI approach, IEEE Trans. Circuits Syst.53(2006)837-842.
- [8] V.cingh, "Some remarks on global asymptotic of neural networks with constant delay," Chaos Fractals 32(5)(2007)1720-1724.
- [9] H.Huang, J.D.Cao. "Exponential stability analysis of uncertain stochastic neural networks with multiple delays." Nonlinear Anal.8(2)(2007)646-653.
- [10] X.M.Zhang, M.Wu, J.H.she, "Delay-dependent stabilization of linear systems with time-varying state and input delaays," Automatica 41 (2005) 1405-1412.
- [11] Z. Wang, D.W.C.Ho, X.Liu, "State estimation for delayed neural networks," IEEE Trans. Neural Netw.16 (2005)279C284.
- [12] H.Wang, Q.Song, "State estimation for neural networks with mixed interval time-varying delays," Neurocomputing. 73 (2010)1281-1288.
- [13] H.Huang, G.Feng, J.Cao," An LMI approach to delay-dependent state estimation for delayed neural networks," Neurocomputing, 71 (2008) 2857-2867.
- [14] T.Li,S.M.Fei,Q.Zhu, "Design of exponential state estimator for neural networks with distributed delays," Nonlinear Anal. Real World Appl. 10(2009)1229-1242.
- [15] M.S. Mahmoud, "New exponentially convergent state estimation method for delayed neural networks." Neurocomputing, 72 (2009) 3935-3942.
- [16] Z.Wang, Y.Liu, X.Liu, "State estimation for jumping recurrent neural networks with discrete and distributed delays." Neural Netw.22 (2009)41-48.
- [17] P. Balasubramaniam,S. Lakshmanan Jeeva Sathya Theesar, S. Jeeva Sathya Theesar, "State estimation for Markovian jumping recurrent neural networks with interval time-varying delays." Nonlinear Dynam.,60 (2009) 661-675.
- [18] Y.Liu, Z.Wang, X.Liu, "Design of exponential state estimators for neural networks with mixed time delays." Phys.Lett.A, 364 (2007) 401-412.
- [19] C. K. Ahn. "Delay-dependent state estimation for T-S fuzzy delayed Hopfield neural networks," Nonlinear Dynam.61 (2010)483-489.
- [20] Y.Chen, W.Bi, W.Li, Y.Wu, "Less conservative results of state estimation for neural networks with time-varying delay." Neurocomputing, 73 (2010) 1324-1331.
- [21] J.H.Park,O.M.Kwon, "Design of state estimator for neural networks of neutral-type." Appl. Math. Comput.202(2008)360-369
- [22] Lin Shi, Hong Zhu, Shouming Zhong, Liyuan Hou, "Globally exponential stability for neural networks with time-varying delays." Applied Mathematics and Computation 219 (2013) 10487-10498.
- [23] K.Gu,"An integral inequality in the stability promblem of time delay systems," in:Proceedings of 39th IEEE Conference Decision Control, 2000.2805-2810.

- [24] O.M.Kwon,J.H.Park,S.M.Lee,"An improved delay-dependent criterion for asymptotic stability of uncertain dynamic systems with time-varying delays," J.Optim.Theory Appl.Math.Comput.218(2012)6762-6775.
- [25] S.Lakshmannan, Ju H. Park, H.Y.Jung, "Design of state estimator for neural networks with leakage, discrete and distributed delays," Applied Mathematices and computation 218 (2012) 11297-11310.
- [26] H.wang, Q.song, "state estimation for neural networks with mixed interval time-varying delays," Neuromputing 73(2010)1281-1288.
- [27] T.Li,S.M.Fei,Q.Zhu, "Design of exponential state estimator for neural networks with distributed delays," Nonlinear Anal.Real World Appl. 10(2009)1229-1242.
- [28] Y.Liu, Z.Wang, X.Liu, "Design of exponential state estimators for neural networks with mixed time delay," Phys.Lett, A 364(2007)401-412.
- [29] Y.Chen, W.Bi, W.Li, Y.Wu, "Less conservation result of state estimation for neural networks with time-varying delay," Neurocomputing 73 (2010) 1324-1331.
- [30] Y,R.Liu,Z.D.Wang,X.H.Liu, "Design of exponential state estimators for neural networks with mixed time delays," Phys.Lett.A 364(5)(2007)401-412.
- [31] P.Gahinet, A.Nemirovsky, A.J.Lau, M.Chilali, LMI Control Toolbox: For Use with Matlab, The MATH Works Inc, 1995.
- [32] Z.D.Wang, Daniel W.C.Ho, X.H.Liu, "State estimation for delayed neural networks," IEEE Trans. Neural Netw. 16(1)(2005)279-284.
- [33] Y.He, Q.G.Wang, M.Wu, C.Lin, "Delay-dependent state estimation for delayed neural networks," IEEE Trans, Neural Netw, 17 (4) (2006) 1077-1081.
- [34] Tao.Li,Shu-min Fei,Qing Zhu, "Design of exponential stste estimator for neural networks with distributed delays," Nonlinear Analysis:Real World Applications 109(2009)1229-1242.
- [35] C.Corduneanu, Principles of Differential and Integral Equations, Allyn and Bacon, Boston, 1971.

**Liyuan Wang** was born in Hebei Province, China,in 1987. She received the B.S. degree from Tangshan Normal University in 2012. She currently pursuing the M.S.degree from University of Electronic Science and Technology of China. Her research interests include the stability of neural networks and the state estimator of neural networks.

Shouming Zhong was born in 1955 in Sichuan, China. He received B.S. degree in applied mathematics from UESTC, Chengdu, China, in 1982. From 1984 to 1986, he studied at the Department of Mathematics in Sun Yatsen University, Guangzhou, China. From 2005 to 2006, he was a visiting research associate with the Department of Mathematics in University of Waterloo, Waterloo, Canada. Heis currently as a full professor with School of Applied Mathematics, UESTC. His current research interests include differential equations, neural networks, biomathematics and robustcontrol. He has authored more than 80 papers in reputed journals such as the International Journal of Systems Science, Applied Mathematics and Computation, Chaos, Solitons and Fractals, Dynamics of Continuous, Discrete and Impulsive Systems, Acta Automatica Sinica, Journal of Control Theory and Applications, Acta Electronica Sinica, Control and Decision, and Journal of Engineering Mathematics.